

Test Report issued under the responsibility of:



TEST REPORT

IEC 62368-1

Audio/video, information and communication technology equipment Part 1: Safety requirements

Report Number:	180301431SHA-001
Date of issue:	2018-09-18
Total number of pages:	92
Applicant's name:	GlobTek, Inc.
Address:	186 VETERANS DRIVE NORTHVALE NJ 07647 USA
Test specification:	
Standard:	IEC 62368-1:2014 (Second Edition)
Test procedure:	CB Scheme
Non-standard test method:	N/A
Test Report Form No	IEC62368_1B
Test Report Form(s) Originator:	UL(US)
Master TRF	2014-03

Copyright © 2014 Worldwide System for Conformity Testing and Certification of Electrotechnical Equipment and Components (IECEE), Geneva, Switzerland. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the IECEE is acknowledged as copyright owner and source of the material. IECEE takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

If this Test Report Form is used by non-IECEE members, the IECEE/IEC logo and the reference to the CB Scheme procedure shall be removed.

This report is not valid as a CB Test Report unless signed by an approved CB Testing Laboratory and appended to a CB Test Certificate issued by an NCB in accordance with IECEE 02.

General disclaimer:

The test results presented in this report relate only to the object tested.

This report shall not be reproduced, except in full, without the written approval of the Issuing CB Testing Laboratory. The authenticity of this Test Report and its contents can be verified by contacting the NCB, responsible for this Test Report.

Page 2 of 92

Report No. 180301431SHA-001

Test Item description	: ITE POWER SUPPLY
Trade Mark (GlobTek)	
Manufacturer	: Same as applicant
Model/Type reference	
Ratings	: Input : 100-240V~,50-60Hz,0.3A Output: 5-5.2VDC, Max.2A, Max 10W
Testing procedure and testing location:	
CB Testing Laboratory:	Intertek Testing Services Shanghai
Testing location/ address	.: Building No. 86, 1198 Qinzhou Road (North) 200233 Shanghai CHINA
Associated CB Testing Laboratory:	
Testing location/ address	.:
Tested by (name + signature)	.: Frank Zhu (Engineer) Trank Zhu
Approved by (name + signature)	.: Jacky Shu (Mandated Reviewer)
Testing procedure: TMP/CTF Stage	1
Testing location/ address	.:
Tested by (name + signature)	.:
Approved by (name + signature)	.:
Testing procedure: WMT/CTF Stage	2
Testing location/ address	
Tested by (name + signature)	
Witnessed by (name + signature)	
Approved by (name + signature)	
Testing procedure: SMT/CTF Stage or 4	3
Testing location/ address	
Tested by (name + signature)	:
Approved by (name + signature)	:
Supervised by (name + signature)	:





Page 4 of 92

TEST ITEM PARTICULARS:	
Classification of use by	Ordinary person
	Children likely to be present
Supply Connection	
Supply Connection	External Circuit - not Mains connected
	$- \square ES1 \square ES2 \boxtimes ES3$
Supply % Tolerance	⊠ +10%/-10%
	☐ +20%/-15%
	□ +%/%
	None
Supply Connection – Type:	⊠ pluggable equipment type A -
	non-detachable supply cord
	☐ appliance coupler
	Diluggable equipment type B -
	non-detachable supply cord
	appliance coupler
	permanent connection
Considered current rating of protective device as part	16A (20A for Noth America)
Equipment mobility:	movable hand-held transportable stationary for building-in direct plug-in rack-mounting wall-mounted
Over voltage category (OVC):	□ OVC I □ OVC II □ OVC III □ OVC IV □ other:
Class of equipment	🗌 Class I 🛛 Class II 🗌 Class III
Access location	\Box restricted access location \boxtimes N/A
Pollution degree (PD)	□ PD 1
Manufacturer's specified maxium operating ambient:	40°C
IP protection class:	
Power Systems	⊠ TN ⊠ TT □ IT V L-L
Altitude during operation (m)	□ 2000 m or less ⊠ 5000 m
Altitude of test laboratory (m)	□ 2000 m or less ⊠ 50 m
Mass of equipment (kg)	Approx. 0.046kg
POSSIBLE TEST CASE VERDICTS:	
- test case does not apply to the test object	Ν/Α
- test object does meet the requirement	P (Pass)





- test object does not meet the requirement	F (Fail)		
TESTING:			
Date of receipt of test item:	2017-10-30		
Date (s) of performance of tests	2017-10-30 to 2018-03-01, 2018-03-16 to 2018-06-22		
GENERAL REMARKS:			
"(See Enclosure #)" refers to additional information appended to the report. "(See appended table)" refers to a table appended to the report.			
Throughout this report a 🗌 comma / 🖂 point is used as the decimal separator.			
Determination of the test result includes consideration of measurement uncertainty from the test			
equipment and methods.			
This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between			

Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to permit copying or distribution of this report and then only in its entirety. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results in this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.

The samples submitted from for evaluation are representative of the products from each factory.

Manufacturer's Declaration per sub-clause 4.2.5 of IECEE 02:

The application for obtaining a CB Test Certificate includes more than one factory location and a declaration from the Manufacturer stating that the sample(s) submitted for evaluation is (are) representative of the products from each factory has been provided	⊠ Yes □ Not applicable
When differences exist; they shall be identified in th	ne General product information section.
Name and address of factory (ies)	1.GlobTek, Inc.
	186 VETERANS DRIVE NORTHVALE NJ 07647 USA
	2.GlobTek (Suzhou) Co., Ltd
	Building 4, No. 76 JinLing East Road, Suzhou Industrial Park, Suzhou, JiangSu, 215021, China



GENERAL PRODUCT INFORMATION:

Product Description -

Product covered by this report is ITE power supply module. GT*86100-**-W2** series for Limited Power Source (LPS) application.

Direct plug-in power supplies are provided with suitable external enclosure. The external enclosure and plug holder parts of the enclosure are ultrasonic welded.

The power supplies are rated class II equipment.

GT*86100-**-W2**:

The 1st "*" part can be 'M' or '-' or 'H' for market identification and not related to safety. The 2nd"*" denotes the rated output wattage designation, which can be "01" to "10", with interval of 1. The 3rd "*" denotes the rated output voltage designation, which can be "05", "5.1", "5.2" or "05", "05.1", "05.2". The 4th"*" designates type of plug and can be E for European plug ,U for British plug, blank for North American /Japan plug/Taiwan plug, C for China plug, A for Australia plug, K for Korea plug. The 5th "*" can be "-USB" or blank, -USB denote the power supplies use USB port, when it is blank, denote the power supplies use DC output wires.

Models GTM86100-1005-W2E-USB and GTM86100-1005-W2A are tested as typical models, model differences were also considered in this report.

Model	Output Voltage	Max. output current	Max. output power
GT*86100-**-W2**	5-5.2VDC	2A	10W
GTM86100-1005-W2E- USB	5VDC	2A	10W
GTM86100-1005-W2A	5VDC	2A	10W

All models were evaluated for maximum manufacturer's recommended ambient of 40 °C.

Model Differences

All models have the similar circuit schematic, components, critical components and also the similar construction. The difference is minor secondary circuit, plug type, output ratings and output wires.

Additional application considerations – (Considerations used to test a component or sub-assembly) N/A



ENERGY SOURCE IDENTIFICATION AND CLASSIFICATION TABLE:			
(Note 1: Identify the following six (6) energy source forms based on the origin of the energy.) (Note 2: The identified classification e.g., ES2, TS1, should be with respect to its ability to cause pain or injury on the body or its ability to ignite a combustible material. Any energy source can be declared Class 3 as a worse case classification e.g. PS3, ES3.			
Electrically-caused injury (Clause 5):			
(Note: Identify type of source, list sub-assembly or circuit d classification)	esignation and corresponding energy source		
	Company and the school (FO)		
	Corresponding classification (ES)		
	ES3		
USB output circuit	ES1		
Electrically-caused fire (Clause 6): (Note: List sub-assembly or circuit designation and corresp Example: Battery pack (maximum 85 watts):	onding energy source classification) PS2		
Source of power or PIS	Corresponding classification (PS)		
All circuits except USB output circuit	PS3		
USB output circuit	PS1		
(Note: Specify hazardous chemicals, whether produces ozone or other chemical construction not addressed as part of the component evaluation.) Example: Liquid in filled component Glycol			
Source of hazardous substances	Corresponding chemical		
N/A	N/A		
Mechanically-caused injury (Clause 8) (Note: List moving part(s), fan, special installations, etc. & corresponding MS classification based on Table 35.) Example: Wall mount unit MS2			
Source of kinetic/mechanical energy	Corresponding classification (MS)		
Sharp edges and corners	MS1		
Equipment mass	MS1		
Thermal burn injury (Clause 9) (Note: Identify the surface or support, and corresponding energy source classification based on type of part, location, operating temperature and contact time in Table 38.) Example: Hand-held scanner – thermoplastic enclosure TS1			
Source of thermal energy	Corresponding classification (TS)		
Accessible enclosure surface	TS1		
Radiation (Clause 10)			
(Note: List the types of radiation present in the product and the corresponding energy source classification.) Example: DVD – Class 1 Laser Product RS1			
Type of radiation	Corresponding classification (RS)		
LED indicator	RS1		

OVERVIEW OF EMPLOYED SAFEGUARDS				
Clause	Possible Hazard			
5.1	Electrically-caused injury			
Body Part	Energy Source	Safeguards		
(e.g. Ordinary)	(ES3: Primary Filter circuit)	Basic	Supplementary	Reinforced (Enclosure)
Ordinary	ES3: input circuit	-	-	Enclosure
Ordinary	ES1:PSU output circuit	-	-	-
6.1	Electrically-caused fire			
Material part	Energy Source		Safeguards	-
(e.g. mouse enclosure)	(PS2: 100 Watt circuit)	Basic	Supplementary	Reinforced
Plastic enclosure	PS3: All circuits except USB output circuit	No excessive temperature	Plastic enclosure used as fire enclosure.	-
USB port	PS1: USB output circuit	-	-	-
7.1	Injury caused by hazardou	us substances		
Body Part	Energy Source		Safeguards	
(e.g., skilled)	(hazardous material)	Basic	Supplementary	Reinforced
-	-	-	-	-
8.1	Mechanically-caused injur	у		
Body Part	Energy Source		Safeguards	1
(e.g. Ordinary)	Lamp)	Basic	Supplementary	Reinforced (Enclosure)
Ordinary	MS1: sharp edges and corners of EUT	-	-	-
Ordinary	MS1: Equipment mass	-	-	-
9.1	Thermal Burn			
Body Part	Energy Source		Safeguards	
(e.g., Ordinary)	(152)	Basic	Supplementary	Reinforced
Ordinary	TS1: Accessible enclosure surface	-	-	-
10.1	Radiation			
Body Part	Energy Source		Safeguards	
(e.g., Ordinary) (Output from audio port)	Basic	Supplementary	Reinforced	
Ordinary	RS1: LED indicator	-	-	-
Supplementary Information: (1) See attached energy source diagram for additional details. (2) "N" – Normal Condition; "A" – Abnormal Condition; "S" Single Fault				



Page 10 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict

4	GENERAL REQUIREMENTS		Р
4.1.1	Acceptance of materials, components and subassemblies	(see appended table 4.1.2)	Р
4.1.2	Use of components		Р
4.1.3	Equipment design and construction		Р
4.1.15	Markings and instructions	(See Annex F)	Р
4.4.4	Safeguard robustness		Р
4.4.4.2	Steady force tests	(See Annex T.5)	Р
4.4.4.3	Drop tests:	(See Annex T.5)	Р
4.4.4.4	Impact tests:		N/A
4.4.4.5	Internal accessible safeguard enclosure and barrier tests		N/A
4.4.4.6	Glass Impact tests		N/A
4.4.4.7	Thermoplastic material tests	70°C,7h	Р
4.4.4.8	Air comprising a safeguard		N/A
4.4.4.9	Accessibility and safeguard effectiveness		Р
4.5	Explosion		N/A
4.6	Fixing of conductors		Р
4.6.1	Fix conductors not to defeat a safeguard		Р
4.6.2	10 N force test applied to	components	Р
4.7	Equipment for direct insertion into mains socket - outlets		Р
4.7.2	Mains plug part complies with the relevant standard	Meet the requirements of relevant mains plug standard.	Р
4.7.3	Torque (Nm):	0.02Nm(EU type)	Р
		0.04Nm(AU type)	
4.8	Products containing coin/button cell batteries		N/A
4.8.2	Instructional safeguard		N/A
4.8.3	Battery Compartment Construction		N/A
	Means to reduce the possibility of children removing the battery:		—
4.8.4	Battery Compartment Mechanical Tests:		N/A
4.8.5	Battery Accessibility		N/A
4.9	Likelihood of fire or shock due to entry of conductive object	(See Annex P)	Р

5	ELECTRICALLY-CAUSED INJURY		Р
5.2.1	Electrical energy source classifications:	(see appended table 5.2)	Р

Total Quality. Assured.

Page 11 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
5.2.2	ES1, ES2 and ES3 limits		Р
5.2.2.2	Steady-state voltage and current:	(see appended table 5.2)	Р
5.2.2.3	Capacitance limits:	60V	Р
5.2.2.4	Single pulse limits		N/A
5.2.2.5	Limits for repetitive pulses:		N/A
5.2.2.6	Ringing signals:		N/A
5.2.2.7	Audio signals:		N/A
5.3	Protection against electrical energy sources		Р
5.3.1	General Requirements for accessible parts to ordinary, instructed and skilled persons		Р
5.3.2.1	Accessibility to electrical energy sources and safeguards		Р
5.3.2.2	Contact requirements		Р
	a) Test with test probe from Annex V	Not contact a bare internal conductive part.	Р
	b) Electric strength test potential (V):		N/A
	c) Air gap (mm):	Min. 2mm	Р
5.3.2.4	Terminals for connecting stripped wire		N/A
5.4	Insulation materials and requirements		Р
5.4.1.2	Properties of insulating material		Р
5.4.1.3	Humidity conditioning:	See clause 5.4.8	Р
5.4.1.4	Maximum operating temperature for insulating materials:	(see appended table 5.4.1.4)	Р
5.4.1.5	Pollution degree:	PD2	
5.4.1.5.2	Test for pollution degree 1 environment and for an insulating compound		N/A
5.4.1.5.3	Thermal cycling		N/A
5.4.1.6	Insulation in transformers with varying dimensions		N/A
5.4.1.7	Insulation in circuits generating starting pulses		N/A
5.4.1.8	Determination of working voltage		Р
5.4.1.9	Insulating surfaces		Р
5.4.1.10	Thermoplastic parts on which conductive metallic parts are directly mounted		N/A
5.4.1.10.2	Vicat softening temperature:		N/A
5.4.1.10.3	Ball pressure:	Plug holder:125°C,1.2mm	Р
5.4.2	Clearances		Р
5.4.2.2	Determining clearance using peak working voltage		Р



Total Quality. Assured.

Page 12 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
5.4.2.3	Determining clearance using required withstand voltage:	(see appended table 5.4.2.3)	Р
	a) a.c. mains transient voltage:	2500V	
	b) d.c. mains transient voltage:		
	c) external circuit transient voltage:		
	d) transient voltage determined by measurement		
5.4.2.4	Determining the adequacy of a clearance using an electric strength test		N/A
5.4.2.5	Multiplication factors for clearances and test voltages:	1.48	Р
5.4.3	Creepage distances:	(see appended table 5.4.2.2, 5.4.2.4 and 5.4.3)	Р
5.4.3.1	General		Р
5.4.3.3	Material Group:	IIIb	
5.4.4	Solid insulation		Р
5.4.4.2	Minimum distance through insulation:	0.4mm	Р
5.4.4.3	Insulation compound forming solid insulation		N/A
5.4.4.4	Solid insulation in semiconductor devices		N/A
5.4.4.5	Cemented joints		N/A
5.4.4.6	Thin sheet material		Р
5.4.4.6.1	General requirements		Р
5.4.4.6.2	Separable thin sheet material		Р
	Number of layers (pcs):	2	Р
5.4.4.6.3	Non-separable thin sheet material		N/A
5.4.4.6.4	Standard test procedure for non-separable thin sheet material:		N/A
5.4.4.6.5	Mandrel test		N/A
5.4.4.7	Solid insulation in wound components		N/A
5.4.4.9	Solid insulation at frequencies >30 kHz:		N/A
5.4.5	Antenna terminal insulation		N/A
5.4.5.1	General		N/A
5.4.5.2	Voltage surge test		N/A
	Insulation resistance (MΩ)		
5.4.6	Insulation of internal wire as part of supplementary safeguard:		N/A
5.4.7	Tests for semiconductor components and for cemented joints		N/A
5.4.8	Humidity conditioning		Р



Total Quality. Assured.

Page 13 of 92

Report No. 180301431SHA-001

IEC 62368-1			
Clause	Requirement + Test	Result - Remark	Verdict
	Relative humidity (%):	93%	
	Temperature (°C):	40°C	
	Duration (h):	120h	
5.4.9	Electric strength test:	(see appended table 5.4.9)	Р
5.4.9.1	Test procedure for a solid insulation type test		Р
5.4.9.2	Test procedure for routine tests		N/A
5.4.10	Protection against transient voltages between external circuit		N/A
5.4.10.1	Parts and circuits separated from external circuits		N/A
5.4.10.2	Test methods		N/A
5.4.10.2.1	General		N/A
5.4.10.2.2	Impulse test:		N/A
5.4.10.2.3	Steady-state test:		N/A
5.4.11	Insulation between external circuits and earthed circuitry:		N/A
5.4.11.1	Exceptions to separation between external circuits and earth		N/A
5.4.11.2	Requirements		N/A
	Rated operating voltage Uop (V):		
	Nominal voltage U _{peak} (V):		
	Max increase due to variation Usp		
	Max increase due to ageing ΔU_{sa} :		
	U_{op} = U_{peak} + ΔU_{sp} + ΔU_{sa} :		
5.5	Components as safeguards		Р
5.5.1	General		Р
5.5.2	Capacitors and RC units		Р
5.5.2.1	General requirement		Р
5.5.2.2	Safeguards against capacitor discharge after disconnection of a connector:	V _{t=2sec} =3.8V; т=28ms	Р
5.5.3	Transformers		Р
5.5.4	Optocouplers		N/A
5.5.5	Relays		N/A
5.5.6	Resistors		N/A
5.5.7	SPD's		Р
5.5.7.1	Use of an SPD connected to reliable earthing		N/A
5.5.7.2	Use of an SPD between mains and protective earth		N/A

Total Quality. Assured.

Page 14 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
5.5.8	Insulation between the mains and external circuit consisting of a coaxial cable:		N/A
5.6	Protective conductor		N/A
5.6.2	Requirement for protective conductors		N/A
5.6.2.1	General requirements		N/A
5.6.2.2	Colour of insulation		N/A
5.6.3	Requirement for protective earthing conductors		N/A
	Protective earthing conductor size (mm ²)		
5.6.4	Requirement for protective bonding conductors		N/A
5.6.4.1	Protective bonding conductors		N/A
	Protective bonding conductor size (mm ²):		
	Protective current rating (A) :		
5.6.4.3	Current limiting and overcurrent protective devices		N/A
5.6.5	Terminals for protective conductors		N/A
5.6.5.1	Requirement		N/A
	Conductor size (mm2), nominal thread diameter (mm).		N/A
5.6.5.2	Corrosion		N/A
5.6.6	Resistance of the protective system		N/A
5.6.6.1	Requirements		N/A
5.6.6.2	Test Method Resistance (Ω):		N/A
5.6.7	Reliable earthing		N/A
5.7	Prospective touch voltage, touch current and prote	ctive conductor current	Р
5.7.2	Measuring devices and networks		Р
5.7.2.1	Measurement of touch current	From L/N to enclosure: 0.005mA From L/N to output:0.087mA	Р
5.7.2.2	Measurement of prospective touch voltage		N/A
5.7.3	Equipment set-up, supply connections and earth connections		N/A
	System of interconnected equipment (separate connections/single connection):		
	Multiple connections to mains (one connection at a time/simultaneous connections)		
5.7.4	Earthed conductive accessible parts		N/A
5.7.5	Protective conductor current		N/A
	Supply Voltage (V):		
	Measured current (mA):		

Page 15 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	Instructional Safeguard	-	N/A
5.7.6	Prospective touch voltage and touch current due to external circuits		N/A
5.7.6.1	Touch current from coaxial cables		N/A
5.7.6.2	Prospective touch voltage and touch current from external circuits		N/A
5.7.7	Summation of touch currents from external circuits		N/A
	a) Equipment with earthed external circuits Measured current (mA)		N/A
	b) Equipment whose external circuits are not referenced to earth. Measured current (mA):		N/A

6	ELECTRICALLY- CAUSED FIRE		Р
6.2	Classification of power sources (PS) and potential ig	gnition sources (PIS)	Р
6.2.2	Power source circuit classifications	All circuits are classified as PS3	Р
6.2.2.1	General		Р
6.2.2.2	Power measurement for worst-case load fault :	(See appended table 6.2.2)	Р
6.2.2.3	Power measurement for worst-case power source fault:	(See appended table 6.2.2)	Р
6.2.2.4	PS1:		N/A
6.2.2.5	PS2:		N/A
6.2.2.6	PS3:	(See appended table 6.2.2)	Р
6.2.3	Classification of potential ignition sources		Р
6.2.3.1	Arcing PIS:		N/A
6.2.3.2	Resistive PIS:	All components in internal circuits are regarded as Resistive PIS.	Р
6.3	Safeguards against fire under normal operating and	abnormal operating conditions	Р
6.3.1 (a)	No ignition and attainable temperature value less than 90 % defined by ISO 871 or less than 300 °C for unknown materials:	(See appended table 5.4.1.5, 6.3.2, 9.0, B.2.6)	Р
6.3.1 (b)	Combustible materials outside fire enclosure		N/A
6.4	Safeguards against fire under single fault conditions	3	Р
6.4.1	Safeguard Method	Control fire spread method.	Р
6.4.2	Reduction of the likelihood of ignition under single fault conditions in PS1 circuits		N/A
6.4.3	Reduction of the likelihood of ignition under single fault conditions in PS2 and PS3 circuits		N/A
6.4.3.1	General		N/A
6.4.3.2	Supplementary Safeguards		N/A

Page 16 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	Special conditions if conductors on printed boards are opened or peeled		N/A
6.4.3.3	Single Fault Conditions :		N/A
	Special conditions for temperature limited by fuse		N/A
6.4.4	Control of fire spread in PS1 circuits		N/A
6.4.5	Control of fire spread in PS2 circuits		N/A
6.4.5.2	Supplementary safeguards:		N/A
6.4.6	Control of fire spread in PS3 circuit		Р
6.4.7	Separation of combustible materials from a PIS	All internal power sources are enclosed by fire enclosure.	N/A
6.4.7.1	General:		N/A
6.4.7.2	Separation by distance		N/A
6.4.7.3	Separation by a fire barrier		Р
6.4.8	Fire enclosures and fire barriers		Р
6.4.8.1	Fire enclosure and fire barrier material properties		Р
6.4.8.2.1	Requirements for a fire barrier		N/A
6.4.8.2.2	Requirements for a fire enclosure		Р
6.4.8.3	Constructional requirements for a fire enclosure and a fire barrier		Р
6.4.8.3.1	Fire enclosure and fire barrier openings		Р
6.4.8.3.2	Fire barrier dimensions		N/A
6.4.8.3.3	Top Openings in Fire Enclosure: dimensions (mm)	No opening.	Р
	Needle Flame test		N/A
6.4.8.3.4	Bottom Openings in Fire Enclosure, condition met a), b) and/or c) dimensions (mm)	No opening.	Р
	Flammability tests for the bottom of a fire enclosure		N/A
6.4.8.3.5	Integrity of the fire enclosure, condition met: a), b) or c):		N/A
6.4.8.4	Separation of PIS from fire enclosure and fire barrier distance (mm) or flammability rating	fire enclosures are made of V-0 class material.	Р
6.5	Internal and external wiring	1	N/A
6.5.1	Requirements		N/A
6.5.2	Cross-sectional area (mm ²):		—
6.5.3	Requirements for interconnection to building wiring:		N/A
6.6	Safeguards against fire due to connection to additional equipment		N/A

Page 17 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	External port limited to PS2 or complies with Clause Q.1		N/A

7	INJURY CAUSED BY HAZARDOUS SUBSTANCES		N/A
7.2	Reduction of exposure to hazardous substances	No hazardous chemicals.	N/A
7.3	Ozone exposure		N/A
7.4	Use of personal safeguards (PPE)		N/A
	Personal safeguards and instructions:		_
7.5	Use of instructional safeguards and instructions		N/A
	Instructional safeguard (ISO 7010)		
7.6	Batteries:		N/A

8	MECHANICALLY-CAUSED INJURY	Р
8.1	General	Р
8.2	Mechanical energy source classifications	Р
8.3	Safeguards against mechanical energy sources	Р
8.4	Safeguards against parts with sharp edges and corners	Р
8.4.1	Safeguards	N/A
8.5	Safeguards against moving parts	N/A
8.5.1	MS2 or MS3 part required to be accessible for the function of the equipment	N/A
8.5.2	Instructional Safeguard: :	_
8.5.4	Special categories of equipment comprising moving parts	N/A
8.5.4.1	Large data storage equipment	N/A
8.5.4.2	Equipment having electromechanical device for destruction of media	N/A
8.5.4.2.1	Safeguards and Safety Interlocks	N/A
8.5.4.2.2	Instructional safeguards against moving parts	N/A
	Instructional Safeguard	
8.5.4.2.3	Disconnection from the supply	N/A
8.5.4.2.4	Probe type and force (N)	N/A
8.5.5	High Pressure Lamps	N/A
8.5.5.1	Energy Source Classification	N/A
8.5.5.2	High Pressure Lamp Explosion Test	N/A
8.6	Stability	N/A

Page 18 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause	Requirement + Test	Result - Remark	Verdict
8.6.1	Product classification		N/A
	Instructional Safeguard		
8.6.2	Static stability		N/A
8.6.2.2	Static stability test		N/A
	Applied Force:		
8.6.2.3	Downward Force Test		N/A
8.6.3	Relocation stability test		N/A
	Unit configuration during 10° tilt:		
8.6.4	Glass slide test		N/A
8.6.5	Horizontal force test (Applied Force):		N/A
	Position of feet or movable parts:		
8.7	Equipment mounted to wall or ceiling		N/A
8.7.1	Mounting Means (Length of screws (mm) and mounting surface):		N/A
8.7.2	Direction and applied force:		N/A
8.8	Handles strength		N/A
8.8.1	Classification		N/A
8.8.2	Applied Force		N/A
8.9	Wheels or casters attachment requirements		N/A
8.9.1	Classification		N/A
8.9.2	Applied force:		
8.10	Carts, stands and similar carriers		N/A
8.10.1	General		N/A
8.10.2	Marking and instructions		
	Instructional Safeguard:		
8.10.3	Cart, stand or carrier loading test and compliance		N/A
	Applied force:		
8.10.4	Cart, stand or carrier impact test		N/A
8.10.5	Mechanical stability		N/A
	Applied horizontal force (N)		_
8.10.6	Thermoplastic temperature stability (°C):		N/A
8.11	Mounting means for rack mounted equipment		N/A
8.11.1	General		N/A
8.11.2	Product Classification		N/A
8.11.3	Mechanical strength test, variable N		N/A
8.11.4	Mechanical strength test 250N, including end stops		N/A

IEC62368_1B



Page 19 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
8.12	Telescoping or rod antennas		N/A
	Button/Ball diameter (mm)		_

9	THERMAL BURN INJURY		Р
9.2	Thermal energy source classifications	(See appended table 5.4.1.4)	Р
9.3	Safeguard against thermal energy sources	TS1	Р
9.4	Requirements for safeguards		N/A
9.4.1	Equipment safeguard		N/A
9.4.2	Instructional safeguard:		N/A

10	RADIATION		Р
10.2	Radiation energy source classification		Р
10.2.1	General classification	RS1, LED indicator only.	Р
10.3	Protection against laser radiation		N/A
	Laser radiation that exists equipment:		
	Normal, abnormal, single-fault		N/A
	Instructional safeguard:		
	Tool:		
10.4	Protection against visible, infrared, and UV radiation		N/A
10.4.1	General		N/A
10.4.1.a)	RS3 for Ordinary and instructed persons:		N/A
10.4.1.b)	RS3 accessible to a skilled person		N/A
	Personal safeguard (PPE) instructional safeguard:		
10.4.1.c)	Equipment visible, IR, UV does not exceed RS1.:		N/A
10.4.1.d)	Normal, abnormal, single-fault conditions:		N/A
10.4.1.e)	Enclosure material employed as safeguard is opaque:		N/A
10.4.1.f)	UV attenuation:		N/A
10.4.1.g)	Materials resistant to degradation UV		N/A
10.4.1.h)	Enclosure containment of optical radiation:		N/A
10.4.1.i)	Exempt Group under normal operating conditions:		N/A
10.4.2	Instructional safeguard		N/A
10.5	Protection against x-radiation		N/A
10.5.1	X- radiation energy source that exists equipment:		N/A

Total Quality. Assured.

Page 20 of 92

Report No. 180301431SHA-001

Requirement + Test	Result - Remark	Verdict
Normal, abnormal, single fault conditions		N/A
Equipment safeguards		N/A
Instructional safeguard for skilled person:		N/A
Most unfavourable supply voltage to give maximum radiation:		_
Abnormal and single-fault condition:		N/A
Maximum radiation (pA/kg):		N/A
Protection against acoustic energy sources		N/A
General		N/A
Classification		N/A
Acoustic output, dB(A):		N/A
Output voltage, unweighted r.m.s:		N/A
Protection of persons		N/A
Instructional safeguards:		N/A
Equipment safeguard prevent ordinary person to RS2:		
Means to actively inform user of increase sound pressure:		
Equipment safeguard prevent ordinary person to RS2:		
Requirements for listening devices (headphones, earphones, etc.)		N/A
Corded passive listening devices with analog input		N/A
Input voltage with 94 dB(A) <i>L_{Aeq}</i> acoustic pressure output:		—
Corded listening devices with digital input		N/A
Maximum dB(A):		_
Cordless listening device		N/A
Maximum dB(A):		
	Requirement + TestNormal, abnormal, single fault conditionsEquipment safeguards	Requirement + TestResult - RemarkNormal, abnormal, single fault conditionsEquipment safeguards



Page 21 of 92

Report No. 180301431SHA-001

```
IEC 62368-1
```

Clause Requirement + Test	Result - Remark	Verdict
---------------------------	-----------------	---------

В	NORMAL OPERATING CONDITION TESTS, ABNORMAL OPERATING CONDITION TESTS AND SINGLE FAULT CONDITION TESTS		
B.2	Normal Operating Conditions		Р
B.2.1	General requirements:	(See Test Item Particulars and appended test tables)	Р
	Audio Amplifiers and equipment with audio amplifiers:		N/A
B.2.3	Supply voltage and tolerances		Р
B.2.5	Input test:	(See appended table B.2.5)	Р
B.3	Simulated abnormal operating conditions		Р
B.3.1	General requirements:	(See appended table B.3)	Р
B.3.2	Covering of ventilation openings		N/A
B.3.3	D.C. mains polarity test		N/A
B.3.4	Setting of voltage selector:		N/A
B.3.5	Maximum load at output terminals		N/A
B.3.6	Reverse battery polarity		N/A
B.3.7	Abnormal operating conditions as specified in Clause E.2.		N/A
B.3.8	Safeguards functional during and after abnormal operating conditions	During an abnormal operating, condition that does not lead to a single fault condition, all safeguards are remained effective. After restoration of normal operating conditions, all safeguards are compliant with	Ρ
-		applicable requirements.	
B.4	Simulated single fault conditions	1	Р
B.4.2	Temperature controlling device open or short- circuited		N/A
B.4.3	Motor tests		N/A
B.4.3.1	Motor blocked or rotor locked increasing the internal ambient temperature:		N/A
B.4.4	Short circuit of functional insulation		Р
B.4.4.1	Short circuit of clearances for functional insulation		Р
B.4.4.2	Short circuit of creepage distances for functional insulation		Р
B.4.4.3	Short circuit of functional insulation on coated printed boards		N/A

Page 22 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
B.4.5	Short circuit and interruption of electrodes in tubes and semiconductors		Р
B.4.6	Short circuit or disconnect of passive components		Р
B.4.7	Continuous operation of components		N/A
B.4.8	Class 1 and Class 2 energy sources within limits during and after single fault conditions	During and after single fault conditions, accessible parts do not exceed the relevant energy class and no flame and ignition inside the equipment.	Ρ
B.4.9	Battery charging under single fault conditions :		N/A
С	UV RADIATION		N/A
C.1	Protection of materials in equipment from UV radiation		N/A
C.1.2	Requirements		N/A
C.1.3	Test method		N/A
C.2	UV light conditioning test		N/A
C.2.1	Test apparatus		N/A
C.2.2	Mounting of test samples		N/A
C.2.3	Carbon-arc light-exposure apparatus		N/A
C.2.4	Xenon-arc light exposure apparatus		N/A
D	TEST GENERATORS		N/A
D.1	Impulse test generators		N/A
D.2	Antenna interface test generator		N/A
D.3	Electronic pulse generator		N/A
E	TEST CONDITIONS FOR EQUIPMENT CONTAIN	NING AUDIO AMPLIFIERS	N/A
E.1	Audio amplifier normal operating conditions		N/A
	Audio signal voltage (V)		
	Rated load impedance (Ω):		
E.2	Audio amplifier abnormal operating conditions		N/A
F	EQUIPMENT MARKINGS, INSTRUCTIONS, AND	INSTRUCTIONAL SAFEGUARDS	Р
F.1	General requirements		Р
	Instructions – Language	English checked.	
F.2	Letter symbols and graphical symbols		Р
F.2.1	Letter symbols according to IEC60027-1		Р
F.2.2	Graphic symbols IEC, ISO or manufacturer specific		Р
F.3	Equipment markings		Р
F.3.1	Equipment marking locations		P

Total Quality. Assured.

Page 23 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
F.3.2	Equipment identification markings		Р
F.3.2.1	Manufacturer identification	See marking plate	
F.3.2.2	Model identification:	See marking plate	
F.3.3	Equipment rating markings		Р
F.3.3.1	Equipment with direct connection to mains		Р
F.3.3.2	Equipment without direct connection to mains		N/A
F.3.3.3	Nature of supply voltage	See marking plate	_
F.3.3.4	Rated voltage	See marking plate	
F.3.3.4	Rated frequency:	See marking plate	
F.3.3.6	Rated current or rated power:	See marking plate	
F.3.3.7	Equipment with multiple supply connections		N/A
F.3.4	Voltage setting device		N/A
F.3.5	Terminals and operating devices		N/A
F.3.5.1	Mains appliance outlet and socket-outlet markings		N/A
F.3.5.2	Switch position identification marking		N/A
F.3.5.3	Replacement fuse identification and rating markings		N/A
F.3.5.4	Replacement battery identification marking :		N/A
F.3.5.5	Terminal marking location		N/A
F.3.6	Equipment markings related to equipment classification		Р
F.3.6.1	Class I Equipment		N/A
F.3.6.1.1	Protective earthing conductor terminal		N/A
F.3.6.1.2	Neutral conductor terminal		N/A
F.3.6.1.3	Protective bonding conductor terminals		N/A
F.3.6.2	Class II equipment (IEC60417-5172)		Р
F.3.6.2.1	Class II equipment with or without functional earth		Р
F.3.6.2.2	Class II equipment with functional earth terminal marking		N/A
F.3.7	Equipment IP rating marking:		_
F.3.8	External power supply output marking		N/A
F.3.9	Durability, legibility and permanence of marking		Р
F.3.10	Test for permanence of markings		Р
F.4	Instructions		Р
	a) Equipment for use in locations where children not likely to be present - marking		N/A
	b) Instructions given for installation or initial use		Р



Page 24 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	c) Equipment intended to be fastened in place		N/A
	d) Equipment intended for use only in restricted access area		N/A
	e) Audio equipment terminals classified as ES3 and other equipment with terminals marked in accordance F.3.6.1		N/A
	f) Protective earthing employed as safeguard		N/A
	g) Protective earthing conductor current exceeding ES 2 limits		N/A
	h) Symbols used on equipment		Р
	i) Permanently connected equipment not provided with all-pole mains switch		N/A
j)	j) Replaceable components or modules providing safeguard function		N/A
F.5	Instructional safeguards		Р
	Where "instructional safeguard" is referenced in the test report it specifies the required elements, location of marking and/or instruction		Р
G	COMPONENTS		Р
G.1	Switches		N/A
G.1.1	General requirements		N/A
G.1.2	Ratings, endurance, spacing, maximum load		N/A
G.2	Relays		N/A
G.2.1	General requirements		N/A
G.2.2	Overload test		N/A
G.2.3	Relay controlling connectors supply power		N/A
G.2.4	Mains relay, modified as stated in G.2		N/A
G.3	Protection Devices		Р
G.3.1	Thermal cut-offs		N/A
G.3.1.1a) &b)	Thermal cut-outs separately approved according to IEC 60730 with conditions indicated in a) & b)		N/A
G.3.1.1c)	Thermal cut-outs tested as part of the equipment as indicated in c)		N/A
G.3.1.2	Thermal cut-off connections maintained and secure		N/A
G.3.2	Thermal links		N/A
G.3.2.1a)	Thermal links separately tested with IEC 60691		N/A
G.3.2.1b)	Thermal links tested as part of the equipment		N/A
	Aging hours (H):		
	Single Fault Condition:		

Page 25 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	Test Voltage (V) and Insulation Resistance (Ω). :		
G.3.3	PTC Thermistors		N/A
G.3.4	Overcurrent protection devices		Р
G.3.5	Safeguards components not mentioned in G.3.1 to	o G.3.5	N/A
G.3.5.1	Non-resettable devices suitably rated and marking provided		N/A
G.3.5.2	Single faults conditions:		N/A
G.4	Connectors		N/A
G.4.1	Spacings		N/A
G.4.2	Mains connector configuration		N/A
G.4.3	Plug is shaped that insertion into mains socket- outlets or appliance coupler is unlikely		N/A
G.5	Wound Components		Р
G.5.1	Wire insulation in wound components	(See Annex J)	Р
G.5.1.2 a)	Two wires in contact inside wound component, angle between 45° and 90°		Р
G.5.1.2 b)	Construction subject to routine testing		N/A
G.5.2	Endurance test on wound components		N/A
G.5.2.1	General test requirements		N/A
G.5.2.2	Heat run test		N/A
	Time (s):		
	Temperature (°C):		
G.5.2.3	Wound Components supplied by mains		N/A
G.5.3	Transformers		Р
G.5.3.1	Requirements applied (IEC61204-7, IEC61558- 1/-2, and/or IEC62368-1)	(see appended table 4.1.2)	Р
	Position:	(see appended table 4.1.2)	
	Method of protection:	With external overcurrent protection.	
G.5.3.2	Insulation		Р
	Protection from displacement of windings:	Blocked by margin wall.	
G.5.3.3	Overload test:	(See appended table B.3)	Р
G.5.3.3.1	Test conditions		Р
G.5.3.3.2	Winding Temperatures testing in the unit		Р
G.5.3.3.3	Winding Temperatures - Alternative test method		N/A
G.5.4	Motors		N/A
G.5.4.1	General requirements		N/A
	Position:		

Report No. 180301431SHA-001

IEC 62368-1

Page 26 of 92

Clause	Requirement + Test	Result - Remark	Verdict
G.5.4.2	Test conditions		N/A
G.5.4.3	Running overload test		N/A
G.5.4.4	Locked-rotor overload test		N/A
	Test duration (days):		_
G.5.4.5	Running overload test for d.c. motors in secondary circuits		N/A
G.5.4.5.2	Tested in the unit		N/A
	Electric strength test (V):		_
G.5.4.5.3	Tested on the Bench - Alternative test method; test time (h)		N/A
	Electric strength test (V):		_
G.5.4.6	Locked-rotor overload test for d.c. motors in secondary circuits		N/A
G.5.4.6.2	Tested in the unit		N/A
	Maximum Temperature:		N/A
	Electric strength test (V):		N/A
G.5.4.6.3	Tested on the bench - Alternative test method; test time (h):		N/A
	Electric strength test (V):		N/A
G.5.4.7	Motors with capacitors		N/A
G.5.4.8	Three-phase motors		N/A
G.5.4.9	Series motors		N/A
	Operating voltage		
G.6	Wire Insulation		Р
G.6.1	General		Р
G.6.2	Solvent-based enamel wiring insulation		N/A
G.7	Mains supply cords		N/A
G.7.1	General requirements		N/A
	Туре		
	Rated current (A)		—
	Cross-sectional area (mm ²), (AWG):		
G.7.2	Compliance and test method		N/A
G.7.3	Cord anchorages and strain relief for non- detachable power supply cords		N/A
G.7.3.2	Cord strain relief		N/A
G.7.3.2.1	Requirements		N/A
	Strain relief test force (N):		—

Total Quality. Assured.

Page 27 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
G.7.3.2.2	Strain relief mechanism failure		N/A
G.7.3.2.3	Cord sheath or jacket position, distance (mm):		
G.7.3.2.4	Strain relief comprised of polymeric material		N/A
G.7.4	Cord Entry:		N/A
G.7.5	Non-detachable cord bend protection		N/A
G.7.5.1	Requirements		N/A
G.7.5.2	Mass (g):		
	Diameter (m):		
	Temperature (°C):		
G.7.6	Supply wiring space		N/A
G.7.6.2	Stranded wire		N/A
G.7.6.2.1	Test with 8 mm strand		N/A
G.8	Varistors		Р
G.8.1	General requirements	VDE approved VDR.	Р
G.8.2	Safeguard against shock		Р
G.8.3	Safeguard against fire	1	Р
G.8.3.2	Varistor overload test:		N/A
G.8.3.3	Temporary overvoltage:		N/A
G.9	Integrated Circuit (IC) Current Limiters	·	N/A
G.9.1 a)	Manufacturer defines limit at max. 5A.		N/A
G.9.1 b)	Limiters do not have manual operator or reset		N/A
G.9.1 c)	Supply source does not exceed 250 VA:		
G.9.1 d)	IC limiter output current (max. 5A):		_
G.9.1 e)	Manufacturers' defined drift:		_
G.9.2	Test Program 1		N/A
G.9.3	Test Program 2		N/A
G.9.4	Test Program 3		N/A
G.10	Resistors		N/A
G.10.1	General requirements		N/A
G.10.2	Resistor test		N/A
G.10.3	Test for resistors serving as safeguards between the mains and an external circuit consisting of a coaxial cable		N/A
G.10.3.1	General requirements		N/A
G.10.3.2	Voltage surge test		N/A
G.10.3.3	Impulse test		N/A

Total Quality. Assured.

Page 28 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
G.11	Capacitor and RC units		Р
G.11.1	General requirements		Р
G.11.2	Conditioning of capacitors and RC units		Р
G.11.3	Rules for selecting capacitors		Р
G.12	Optocouplers		N/A
	Optocouplers comply with IEC 60747-5-5:2007 Spacing or Electric Strength Test (specify option and test results)		N/A
	Type test voltage Vini:		_
	Routine test voltage, Vini,b:		
G.13	Printed boards		Р
G.13.1	General requirements		Р
G.13.2	Uncoated printed boards		Р
G.13.3	Coated printed boards		N/A
G.13.4	Insulation between conductors on the same inner surface		N/A
	Compliance with cemented joint requirements (Specify construction):		—
G.13.5	Insulation between conductors on different surfaces		N/A
	Distance through insulation		N/A
	Number of insulation layers (pcs):		
G.13.6	Tests on coated printed boards		N/A
G.13.6.1	Sample preparation and preliminary inspection		N/A
G.13.6.2a)	Thermal conditioning		N/A
G.13.6.2b)	Electric strength test		N/A
G.13.6.2c)	Abrasion resistance test		N/A
G.14	Coating on components terminals		N/A
G.14.1	Requirements:		N/A
G.15	Liquid filled components		N/A
G.15.1	General requirements		N/A
G.15.2	Requirements		N/A
G.15.3	Compliance and test methods		N/A
G.15.3.1	Hydrostatic pressure test		N/A
G.15.3.2	Creep resistance test		N/A
G.15.3.3	Tubing and fittings compatibility test		N/A
G.15.3.4	Vibration test		N/A
G.15.3.5	Thermal cycling test		N/A

Total Quality. Assured.

Page 29 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test Result - Remark	Verdict
G.15.3.6	Force test	N/A
G.15.4	Compliance	N/A
G.16	IC including capacitor discharge function (ICX)	N/A
a)	Humidity treatment in accordance with sc5.4.8 – 120 hours	N/A
b)	Impulse test using circuit 2 with Uc = to transient voltage	N/A
C1)	Application of ac voltage at 110% of rated voltage for 2.5 minutes	N/A
C2)	Test voltage:	
D1)	10,000 cycles on and off using capacitor with smallest capacitance resistor with largest resistance specified by manufacturer	N/A
D2)	Capacitance:	—
D3)	Resistance:	
н	CRITERIA FOR TELEPHONE RINGING SIGNALS	N/A
H.1	General	N/A
H.2	Method A	N/A
H.3	Method B	N/A
H.3.1	Ringing signal	N/A
H.3.1.1	Frequency (Hz)	
H.3.1.2	Voltage (V)	
H.3.1.3	Cadence; time (s) and voltage (V)	
H.3.1.4	Single fault current (mA):	
H.3.2	Tripping device and monitoring voltage:	N/A
H.3.2.1	Conditions for use of a tripping device or a monitoring voltage complied with	N/A
H.3.2.2	Tripping device	N/A
H.3.2.3	Monitoring voltage (V):	
J	INSULATED WINDING WIRES FOR USE WITHOUT INTERLEAVED INSULATION	Р
	General requirements	Р
К	SAFETY INTERLOCKS	N/A
K.1	General requirements	N/A
K.2	Components of safety interlock safeguard mechanism	N/A
K.3	Inadvertent change of operating mode	N/A
K.4	Interlock safeguard override	N/A
K.5	Fail-safe	N/A

Page 30 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	Compliance		N/A
K.6	Mechanically operated safety interlocks		N/A
K.6.1	Endurance requirement		N/A
K.6.2	Compliance and Test method:		N/A
K.7	Interlock circuit isolation		N/A
K.7.1	Separation distance for contact gaps & interlock circuit elements (type and circuit location):		N/A
K.7.2	Overload test, Current (A):		N/A
K.7.3	Endurance test		N/A
K.7.4	Electric strength test:	(See appended table 5.4.11)	N/A
L	DISCONNECT DEVICES		Р
L.1	General requirements		Р
L.2	Permanently connected equipment		N/A
L.3	Parts that remain energized		N/A
L.4	Single phase equipment		Р
L.5	Three-phase equipment		N/A
L.6	Switches as disconnect devices		N/A
L.7	Plugs as disconnect devices		Р
L.8	Multiple power sources		N/A
М	EQUIPMENT CONTAINING BATTERIES AND TH	HEIR PROTECTION CIRCUITS	N/A
M.1	General requirements		N/A
M.2	Safety of batteries and their cells		N/A
M.2.1	Requirements		N/A
M.2.2	Compliance and test method (identify method) :		N/A
M.3	Protection circuits		N/A
M.3.1	Requirements		N/A
M.3.2	Tests		N/A
	- Overcharging of a rechargeable battery		N/A
	- Unintentional charging of a non-rechargeable battery		N/A
	- Reverse charging of a rechargeable battery		N/A
	- Excessive discharging rate for any battery		N/A
M.3.3	Compliance:		N/A
M.4	Additional safeguards for equipment containing secondary lithium battery		N/A
M.4.1	General		N/A
M.4.2	Charging safeguards		N/A

Total Quality. Assured.

Page 31 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
M.4.2.1	Charging operating limits		N/A
M.4.2.2a)	Charging voltage, current and temperature:		
M.4.2.2 b)	Single faults in charging circuitry:		
M.4.3	Fire Enclosure		N/A
M.4.4	Endurance of equipment containing a secondary lithium battery		N/A
M.4.4.2	Preparation		N/A
M.4.4.3	Drop and charge/discharge function tests		N/A
	Drop		N/A
	Charge		N/A
	Discharge		N/A
M.4.4.4	Charge-discharge cycle test		N/A
M.4.4.5	Result of charge-discharge cycle test		N/A
M.5	Risk of burn due to short circuit during carrying		N/A
M.5.1	Requirement		N/A
M.5.2	Compliance and Test Method (Test of P.2.3)		N/A
M.6	Prevention of short circuits and protection from other effects of electric current		N/A
M.6.1	Short circuits		N/A
M.6.1.1	General requirements		N/A
M.6.1.2	Test method to simulate an internal fault		N/A
M.6.1.3	Compliance (Specify M.6.1.2 or alternative method):		N/A
M.6.2	Leakage current (mA):		N/A
M.7	Risk of explosion from lead acid and NiCd batteries		N/A
M.7.1	Ventilation preventing explosive gas concentration		N/A
M.7.2	Compliance and test method		N/A
M.8	Protection against internal ignition from external spark sources of lead acid batteries		N/A
M.8.1	General requirements		N/A
M.8.2	Test method		N/A
M.8.2.1	General requirements		N/A
M.8.2.2	Estimation of hypothetical volume Vz (m ³ /s):		—
M.8.2.3	Correction factors:		—
M.8.2.4	Calculation of distance d (mm):		_
M.9	Preventing electrolyte spillage		N/A



Page 32 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
M.9.1	Protection from electrolyte spillage		N/A
M.9.2	Tray for preventing electrolyte spillage		N/A
M.10	Instructions to prevent reasonably foreseeable misuse (Determination of compliance: inspection, data review; or abnormal testing):		N/A
Ν	ELECTROCHEMICAL POTENTIALS	·	N/A
	Metal(s) used:		—
0	MEASUREMENT OF CREEPAGE DISTANCES A	ND CLEARANCES	Р
	Figures O.1 to O.20 of this Annex applied:	Figures O.1	—
Ρ	SAFEGUARDS AGAINST ENTRY OF FOREIGN INTERNAL LIQUIDS	OBJECTS AND SPILLAGE OF	Р
P.1	General requirements		Р
P.2.2	Safeguards against entry of foreign object		Р
	Location and Dimensions (mm):	No openings exceed 5mm in any dimension.	
P.2.3	Safeguard against the consequences of entry of foreign object		Р
P.2.3.1	Safeguards against the entry of a foreign object		N/A
	Openings in transportable equipment		N/A
	Transportable equipment with metalized plastic parts:		N/A
P.2.3.2	Openings in transportable equipment in relation to metallized parts of a barrier or enclosure (identification of supplementary safeguard):		N/A
P.3	Safeguards against spillage of internal liquids		N/A
P.3.1	General requirements		N/A
P.3.2	Determination of spillage consequences		N/A
P.3.3	Spillage safeguards		N/A
P.3.4	Safeguards effectiveness		N/A
P.4	Metallized coatings and adhesive securing parts		N/A
P.4.2 a)	Conditioning testing		N/A
	Tc (°C):		_
	Tr (°C):		
	Ta (°C):		—
P.4.2 b)	Abrasion testing:		N/A
P.4.2 c)	Mechanical strength testing		N/A
Q	CIRCUITS INTENDED FOR INTERCONNECTION	WITH BUILDING WIRING	Р
Q.1	Limited power sources		Р
Q.1.1 a)	Inherently limited output		Р

Page 33 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
Q.1.1 b)	Impedance limited output		N/A
	- Regulating network limited output under normal operating and simulated single fault condition		N/A
Q.1.1 c)	Overcurrent protective device limited output		N/A
Q.1.1 d)	IC current limiter complying with G.9		N/A
Q.1.2	Compliance and test method		Р
Q.2	Test for external circuits – paired conductor cable		N/A
	Maximum output current (A):		
_	Current limiting method:		_
R	LIMITED SHORT CIRCUIT TEST		N/A
R.1	General requirements		N/A
R.2	Determination of the overcurrent protective device and circuit		N/A
R.3	Test method Supply voltage (V) and short-circuit current (A)).		N/A
S	TESTS FOR RESISTANCE TO HEAT AND FIRE		N/A
S.1	Flammability test for fire enclosures and fire barrier materials of equipment where the steady state power does not exceed 4 000 W		N/A
	Samples, material:		
	Wall thickness (mm):		
	Conditioning (°C):		
	Test flame according to IEC 60695-11-5 with conditions as set out		N/A
_	- Material not consumed completely		N/A
	- Material extinguishes within 30s		N/A
	- No burning of layer or wrapping tissue		N/A
S.2	Flammability test for fire enclosure and fire barrier integrity		N/A
	Samples, material		
	Wall thickness (mm):		
_	Conditioning (°C):		
	Test flame according to IEC 60695-11-5 with conditions as set out		N/A
	Test specimen does not show any additional hole		N/A
S.3	Flammability test for the bottom of a fire enclosure		N/A
	Samples, material:		—
	Wall thickness (mm):		



Page 34 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	Cheesecloth did not ignite		
S.4	Flammability classification of materials		N/A
S.5	Flammability test for fire enclosures and fire barrier materials of equipment where the steady state power does not exceed 4 000 W		N/A
	Samples, material		
	Wall thickness (mm):		
	Conditioning (test condition), (°C):		
	Test flame according to IEC 60695-11-20 with conditions as set out		N/A
	After every test specimen was not consumed completely		N/A
	After fifth flame application, flame extinguished within 1 min		N/A
т	MECHANICAL STRENGTH TESTS		Р
T.1	General requirements		Р
T.2	Steady force test, 10 N	(See appended table T.2)	Р
Т.3	Steady force test, 30 N		N/A
T.4	Steady force test, 100 N		N/A
Т.5	Steady force test, 250 N	(See appended table T.5)	Р
Т.6	Enclosure impact test		N/A
	Fall test		N/A
	Swing test		N/A
T.7	Drop test	(See appended table T.7)	Р
T.8	Stress relief test:	(See appended table T.8)	Р
T.9	Impact Test (glass)		N/A
T.9.1	General requirements		N/A
T.9.2	Impact test and compliance		N/A
	Impact energy (J):		
	Height (m):		
T.10	Glass fragmentation test		N/A
T.11	Test for telescoping or rod antennas		N/A
	Torque value (Nm)		
U	MECHANICAL STRENGTH OF CATHODE RAY T AGAINST THE EFECTS OF IMPLOSION	UBES (CRT) AND PROTECTION	N/A
U.1	General requirements		N/A
U.2	Compliance and test method for non-intrinsically protected CRTs		N/A



Page 35 of 92

Report No. 180301431SHA-001

IEC 62368-1						
Clause	Requirement + Test Result - Remark					
U.3	Protective Screen	(See Annex T)	N/A			
V	DETERMINATION OF ACCESSIBLE PARTS (FINGERS, PROBES AND WEDGES)					
V.1	Accessible parts of equipment		Р			
V.2	Accessible part criterion		Р			

Page 36 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause Red

Requirement + Test

Result - Remark

Verdict

4.1.2	TABLE: List of critical components				Р	
Object / part No.	Manufacturer/ Type / model trademark		Technical data	Standard	Mark(s) of conformity ¹	
- Description ²⁾ :	Main body					
Enclosure (all parts)	SABIC JAPAN L L C	SE1X V-1, Min. thickness: IEC/EN 62368-1 IEC/EN 6236		Tested with appliance UL E207780		
Alt. use	SABIC JAPAN L L C	SE100	V-1, Min. thickness: 1.5mm, 80°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	940	V-0, Min. thickness: 1.5mm, 120°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	CX7211	V-0, Min. thickness: 1.5mm, 90°C	IEC/EN 62368-1 UL 94 UL 746C	52368-1 Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	C2950	V-0, Min. thickness: 1.5mm, 75°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	925U	V-0, Min. thickness: 1.5mm, 115°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	945	V-0, Min. thickness: 1.5mm, 120°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	CH6410	V-0, Min. thickness: 1.5mm, 100°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC JAPAN L L C	EXCY0198	V-0, Min. thickness: 1.5mm, 100°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E207780	
Alt. use	SABIC INNOVATIVE PLASTICS B V	SE1X, SE1	V-1, Min. thickness: 1.5mm,105°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E45329	
Alt. use	SABIC INNOVATIVE PLASTICS B V	C2950	V-0, Min. thickness: 1.5mm, 75°C	IEC/EN 62368-1 UL 94 UL 746C	Tested with appliance UL E45329	



Total Quality. Assured.

Page 37 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test		Result - Remark		Verdict			
Alt. use	SABIC INNOVATIVE PLASTICS B V	CX7211	V-0, Min. thickness: IEC/EN 62368-1 1.5mm, 90°C UL 94 UL 746C		Tested with appliance UL E45329			
Alt. use	SABIC INNOVATIVE PLASTICS B V	945	V-0, Min 1.5mm,	. thickness: 120°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance . E45329	
Alt. use	SABIC INNOVATIVE PLASTICS B V	HF500R	V-0, Min 1.5mm,	. thickness: 125°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance . E45329	
Alt. use	ASAHI KASEI CORPORATION	540V	V-1, Min 1.5mm,	V-1, Min. thickness: IEC/EN 62368-1 1.5mm, 100°C UL 94 UL 746C		Te ap E8	Tested with appliance E82268	
Alt. use	COVESTRO DEUTSCHLAND AG [PC RESINS]	FR6005	V-0, Min 1.5mm,	. thickness: 105°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance . E41613	
Alt. use	COVESTRO DEUTSCHLAND AG [PC RESINS]	6485	V-0, Min. thickness: IEC/EN 62368-1 1.5mm, 115°C UL 94 UL 746C		Te ap UL	sted with pliance . E41613		
Alt. use	IDEMITSU KOSAN CO LTD	AZ2201	V-0, Min 1.5mm,	<i>I</i> in. thickness: IEC/EN 62368-1 n, 125°C UL 94 UL 746C		Te ap UL	sted with pliance E48268	
Plug unit (for EU type) (for model GT*86100-**- W2*-USB (end appliance))	GlobTek INC		2.5A, 250VAC		EN 50075:1900	Re Re 18 HA	efer Intertek eport No. 0501603S A-001	
Plug unit (for AU type) (for model GT*86100-**- W2*-USB (end appliance))	GlobTek INC		10A, 250)VAC	AS/NZS 3112:2011+A1:20 12+A2:2013+A3: 2016	Re Re 18 HA	efer Intertek eport No. 0501604S A-001	
Plug holder	SABIC Japan L L C	SE1X	V-1, Min 1.5mm,	. thickness: 105°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance . E207780	
Alt. use	SABIC JAPAN L L C	945	V-0, Min 1.5mm,	. thickness: 120°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance . E207780	


Page 38 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Re	sult - Remark		Verdict
Alt. use	NAN YA PLASTICS CORP PLASTICS 3RD DIV SABIC	6410G5 SE1X, SE1	V-0, Min 1.5mm,	. thickness: 115°C . thickness:	IEC/EN 62368-1 UL 94 UL 746C IEC/EN 62368-1	Te ap UL Te	ested with pliance E130155
	INNOVATIVE PLASTICS B V	· · · · , · · · ·	1.5mm,	105°C	UL 94 UL 746C	ap UL	pliance E45329
Alt. use	SABIC INNOVATIVE PLASTICS B V	945	V-0, Min 1.5mm,	. thickness: 120°C	IEC/EN 62368-1 UL 94 UL 746C	Te ap UL	sted with pliance E45329
PCB	Shenzhen Wuzhu Tech Co Ltd	WZ-4	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E170968
Alt. use	WALEX ELECTRONIC(WU XI)CO LTD	T2, T2A, T2B, T4	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E154355
Alt. use	DONGGUAN HE TONG ELECTRONICS CO LTD	CEM1, 2V0 FR4	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E243157
Alt. use	Huizhou Shunjia Electronics Co Ltd	SJ-B	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E320884
Alt. use	Cheerful Electronics(HK)Ltd	02,03,03A	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E199724
Alt. use	Dongguan Daysun Electronic Co Ltd	DS2	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E251754
Alt. use	Suzhou City Yilihua Electronics Co Ltd	YLH-1	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E251781
Alt. use	DAFENG AREX ELECTRONICS TECHNOLOGY CO LTD	02V0, 04V0, 03V0	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E186016
Alt. use	BRITE PLUS ELECTRONICS(SU ZHOU)CO LTD	DKV0-3A DGV0-3A	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Te ap UL	ested with pliance - E177671



Page 39 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Re	sult - Remark	Verdict
Alt. use	KUOTIANG ENT LTD	C-2 C-2A	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E227299
Alt. use	SHENZHEN TONGCHUANXIN ELECTRONICS CO LTD	тсх	V-0, 130 Min. 1.0r	°C nm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E250336
Alt. use	PACIFIC WIN INDUSTRIAL LTD	PW-02 PW-03	V-0, 130 Min. 1.0r	°C nm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E228070
Alt. use	YUANMAN PRINTED CIRCUIT CO LTD	1V0	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E74757
Alt. use	SUZHOU XINKE ELECTRONICS CO LTD	ХК-2, ХК-3	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E231590
Alt. use	KUNSHAN CITY HUA SHENG CIRCUIT BOARD CO LTD	HS-S	V-0, 130 Min. 1.0r	°C nm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E229877
Alt. use	JIANGSU DIFEIDA ELECTRONICS CO LTD	DFD-1	V-0, 130 Min. 1.0r	°C mm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E213009
Alt. use	SHANGHAI H- FAST ELECTRONIC CO LTD	211001, 411001	V-0, 130 Min. 1.0r	°C nm	Applicable parts of IEC/EN 62368-1	Tested with appliance UL E337862
Resistor Fuse(RT1)(For mdoel series: GT*86100-**- W2*-USB only)	Anhui Changsheng Electronics Co., Ltd	RXF21-2W	3.3ohm,	2W	IEC/EN 62368-1	VDE 40024768
Alt. use	Shenzhen Great Electronics Co. Ltd.	RXF	3.3ohm,	2W	IEC/EN 62368-1	VDE 40026608
Alt. use	Shenzhen Kayocota Electronics Co., Ltd	FRKNP	3.3ohm,	2W	IEC/EN 62368-1	VDE 40043957
Alt. use	TZAI YUAN Enterprise Co., Ltd	KNF	3.3ohm,	2W	IEC/EN 62368-1	VDE 40035589



Page 40 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Res	sult - Remark		Verdict
Current fuse (F1)	E LITTELFUSE WICKMANN WERKE	392	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC UL)E 126983 . E67006
Alt. use	Ever Island Electric Co., Ltd. & Walter Electric	2010 series	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 018781 . E220181
Alt. use	Shenzhen Lanson Electronics Co. Ltd.	SMT	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 012592 . E221465
Alt. use	Conquer Electronics Co., Ltd.	MST	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 017157 . E82636
Alt. use	Cooper Bussmann LLC	SS-5	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 015513 . E19180
Alt. use	Bel Fuse Ltd.	RST-Serie(s)	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 011144 . E20624
Alt. use	SMART ELECTRONICS INC	SPT	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 014285 . E238986
Alt. use	SUNNY EAST ENTERPRISE CO LTD	TSP series	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL)E 027173 . E133774
Alt. use	Conquer Electronics Co., Ltd.	PTU	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VE 40 UL)E 017157 . E82636



Page 41 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Res	sult - Remark		Verdict
Alt. use	Littelfuse Inc	877	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VD 40 UL	0E 023242 . E10480
Alt. use	NIPPON SEISEN CABLE LTD	SLT	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VD 40 UL	DE 013103 . E120786
Alt. use	Walter Electronic Co. Ltd.	ICP	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VC 40 UL	DE 012824 . E56092
Alt. use	XC ELECTRONICS (SHENZHEN) CORP LTD	5TE	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VD 40 UL	DE 029550 . E249609
Alt. use	XC ELECTRONICS (SHENZHEN) CORP LTD	4T series	T1A or 2 sub-mini	A, 250V ature fuse	IEC 60127-1 IEC 60127-3 UL 248-1 UL 248-14	VD 40 UL	DE 029295 . E249609
Y capacitor (CY1, CY2) (Optional)	TDK-EPC Corporation, Capacitors Group Circuit Devices Business Group	CD	Y1, AC2 2200pF,	50V, max 25/085/21/B	IEC/EN 60384-14 UL 60384-14 UL 1414	VD 40 UL)E 029780 .E37861
Alt. use	Murata Mfg. Co., Ltd.	кх	Y1, AC2 2200pF,	50V, max 25/125/21/B	IEC/EN 60384-14 UL 60384-14 UL 1414	VD 40 UL	0E 002831 . E37921
Alt. use	Success Electronics Co., Ltd.	SE	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VD 40 UL	DE 037211 . E114280
Alt. use	Success Electronics Co., Ltd.	SB	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VD 40 UL	DE 037221 . E114280
Alt. use	JYA-NAY Co., Ltd.	JN	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VD 40 UL	DE 001831 . E201384



Page 42 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Res	sult - Remark		Verdict
Alt. use	WELSON INDUSTRIAL CO LT D	WD	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE 40 UL	DE 016157 . E104572
Alt. use	SAMWHA CAPACITOR CO LTD	SD	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE 40 UL	DE 015804 . E97754
Alt. use	NAN JING YUYUE ELECTRONICS CO LTD	СТ7	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE 40 UL	DE 008010 . E237728
Alt. use	YINAN DON'S ELECTRONIC COMPONENT CO LTD	CT81	Y1, AC2 2200pF,	50V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE	DE 135256 . E145038
Alt. use	JYH CHUNG ELECTRONICS CO LTD	JD	Y1, AC4 2200pF,	00V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE UL	DE 137027 . E187963
Alt. use	JYH CHUNG ELECTRONICS CO LTD.	JY	Y2, AC3 2200pF,	00V, max 30/125/56/C	IEC/EN 60384-14 UL 60384-14 UL 1414	VE UL	DE 137027 . E187963
Transformer (T1)	GlobTek / BOAM / HAOPUWEI / Dee Van Enterprise Co., Ltd.	90E10PFX0- xxxx for Model: GT*86100-**- W2*-USB only; 90E10PF02- xxxx for Model: GT*86100-**- W2* only ("xxxx" to denote the part number, can be any alphanumeric character for marketing purposes only.	Class B		IEC/EN 62368-1	Te	sted with pliance



Page 43 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test	Res		sult - Remark		Verdict
-Bobbin	HITACHI CHEMICAL CO LTD	CP-J-8800	V-0, 150 0.45 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E42956
- Alt. use	SUMITOMO BAKELITE CO LTD	PM-9820	V-0, 150 0.45 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E41429
- Alt. use	SUMITOMO BAKELITE CO LTD	PM-9630	V-0, 150 0.45 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E41429
- Alt. use	CHANG CHUN PLASTICS CO LTD	T375J	V-0, 140 0.74 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E59481
- Alt. use	CHANG CHUN PLASTICS CO LTD	T373J	V-0, 150 0.45 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E59481
- Alt. use	CHANG CHUN PLASTICS CO LTD	T375HF	V-0, 150 0.45 mm	°C, thickness min.	IEC/EN 62368-1 UL 94	Te ap UL	sted with pliance . E59481
- Magnet wire	Golden Ocean	UEW-X	130`C		IEC/EN 62368-1	Te ap UL	sted with pliance E225143
Alt. use	Da Yang	UEW	130°C		IEC/EN 62368-1	Te ap UL	sted with pliance . E176101
Alt. use	Wa Tai	UEW	130°C		IEC/EN 62368-1	Te ap UL	sted with pliance E243939
Alt. use	Feng Ching	UEW	130°C		IEC/EN 62368-1	Te ap UL	sted with pliance . E172395
Alt. use	TAI-I	UEW	130°C		IEC/EN 62368-1	Te ap UL	sted with pliance E234896
Alt. use	NINGBO JINTIAN NEW MATERIAL CO LTD	2UEW	155ºC		IEC/EN 62368-1	Te ap UL	sted with pliance E227047
-Triple- insulated wire (Secondary)	Furukawa Electric Co., Ltd.	TEX-E	Class B, insulation	reinforced n	IEC/EN 62368-1 UL 2353	VC UL	DE 006735 . E206440



Page 44 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Res	sult - Remark		Verdict
- Alt. use	SUZHOU YUSHENG ELECTRONIC CO LTD	TIW-B,TWE-3	Class B, insulation	reinforced n	IEC/EN 62368-1 UL 2353	VC 40 UL	DE 033527 . E332529
- Alt. use	DAH JIN TECHNOLOGY CO LTD	TLW-B	Class B, insulation	reinforced n	ed IEC/EN 62368-1 UL 2353		DE 019324 . E236542
- Alt. use	COSMOLINK CO. Ltd.	TIW-M	Class B, insulation	reinforced n	IEC/EN 62368-1 UL 2353	VE UL	DE 138053 . E213764
- Alt. use	YOUNG CHANG SILICONE CO LTD	STW-B	Class B, insulation	reinforced n	IEC/EN 62368-1 UL 2353	VE 40 UL	DE 013359 . E303298
- Alt. use	Great Leoflon TRW (B) Class B, reinforced insulation		reinforced	IEC/EN 62368-1 UL 2353	VE UL	DE 136581 . E211989	
- Alt. use	E&B TECHNOLOGY CO LTD	E&B-B-X.XX	Reinforc Class B	ed insulation,	IEC/EN 62368-1 UL 2353	VE 40 UL	DE 023473 . E315265
- Alt. use	DONGGUAN KOSHEN INSULATOR CO LTD	ТIW-В	Reinforc Class B	ed insulation,	IEC/EN 62368-1 UL 2353	Te ap UL	sted with pliance . E365580
-Insulating tape	SYMBIO INC	35660,35661, 35660Y	130°C		IEC/EN 62368-1 UL 510	Te ap UL	sted with pliance . E50292
- Alt. use	3M COMPANY ELECTRICAL MARKETS DIV (EMD)	1350F-1, 1350T-1	130°C		IEC/EN 62368-1 UL 510	Te ap UL	sted with pliance . E17385
- Alt. use	BONDTEC PACIFIC CO LTD	370S	130°C		IEC/EN 62368-1 UL 510	Te ap UL	sted with pliance . E175868
- Alt. use	. use JINGJIANG PZ, 130°C YAHUA CT, PRESSURE SENSITIVE GLUE CO LTD			IEC/EN 62368-1 UL 510	Te ap UL	sted with pliance . E165111	
- Alt. use	JINGJIANG JINGYI ADHESIVE PRODUCT CO LTD	JY25-A	130°C		IEC/EN 62368-1 UL 510	Te ap UL	sted with pliance . E246950



Page 45 of 92

Report No. 180301431SHA-001

Clause	Requirem	ent + Test		Res	ult - Remark	Verdict
- Alt. use	CHANG SHU LIANG YI TAPE INDUSTRY CO LTD	LY-XX	130°C		IEC/EN 62368-1 UL 510	Tested with appliance UL E246820
-PTFE tubing	GREAT HOLDING INDUSTRIAL CO LTD	TFT, TFS	300V, 20	00°C	IEC/EN 62368-1	Tested with appliance UL E156256
-Alt. use	SHENZHEN WOER HEAT- SHRINKABLE MATERIAL CO LTD	WF	600V, 20	00°C	IEC/EN 62368-1	Tested with appliance UL E203950
-Alt. use	CHANGYUAN ELECTRONICS (SHENZHEN) CO LTD	CB-TT-T, CB-TT-S	300V, 20	00°C	IEC/EN 62368-1	Tested with appliance UL E180908
-Alt. use	ZEUS	TFE-TW-300, TFE-SW-600	Min.300	/, 200`C.	IEC/EN 62368-1	Tested with appliance UL E64007
Varistor MOV1 (Optional)(For Model: GT*86100-**- W2* only)	CENTRA SCIENCE CORP	CNR- 10D471K, CNR- 10D511K, CNR- 14D471K, CNR- 14D511K	Min. 300 40/85/56 fulfilled 6 test. V-1.	Vac, , ikV/3kA pulse	IEC 61051-2 IEC 62368-1	VDE 40008220 UL E316325
-Alt. use	Joyin Co Ltd	JVR10N471K, JVR10N511K, JVR14N471K, JVR14N511K	Min. 300 40/85/56 fulfilled 6 test.V-1.	Vac, , ;kV/3kA pulse	IEC 61051-2 IEC 62368-1	VDE 005937
-Alt. use	Fenghua Advanced Technology Holding Co Ltd. Xianhua New Sensitive Components & Sensor Branch Co.	FNR- 10K471K, FNR- 10K511K, FNR- 14K471K, FNR-14K511K	Min. 300 385Vdc, 40/85/56 fulfilled 6 test. V-1.	Vac, min. , ikV/3kA pulse	IEC 61051-2 IEC 62368-1	VDE 40008242



Page 46 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause	Requirem	ent + Test		Res	ult - Remark		Verdict
-Alt. use	Success Electronics Co Ltd	SVR10D471K, SVR10D511K, SVR14D471K, SVR14D511K	Min. 300Vac, min. 385Vdc, 40/85/56, fulfilled 6kV/3kA pulse test.V-1.		IEC 61051-2 IEC 62368-1	VE	DE 123677
-Alt. use	Thinking Electronic Industrial Co Ltd	TVR10471K, TVR10511K, TVR14471K, TVR14511K	Min. 300 385Vdc, 40/85/56 fulfilled 6 test.V-1.	Vac, min. , skV/3kA pulse	IEC 61051-2 IEC 62368-1	VE 40)E 021243
-Alt. use	Brightking Inc.	CNR471KD10, CNR511KD10, CNR471KD14, CNR511KD14	Min. 300 385Vdc, 40/85/56 fulfilled 6 test.V-1.	Vac, min. , skV/3kA pulse	IEC 61051-2 IEC 62368-1	VE 40)E 022070
-Alt. use	Brightking (Shenzhen) Co., Ltd.	14D471K, 14D511K	Min. 300 385Vdc, 40/85/56 fulfilled 6 test.V-1.	Vac, min. , skV/3kA pulse	IEC 61051-2 IEC 62368-1	VE 40)E 027827

Supplementary information:

¹⁾ Provided evidence ensures the agreed level of compliance. See OD-CB2039.

²⁾ Description line content is optional. Main line description needs to clearly detail the component used for testing

5.2	Tab	ole: Cl	assification of e	electrical energy s	ources			Ρ
5.2.2.2 -	- Steady	State	Voltage and Cur	rent conditions				
5.2 Table: Classification of electrical energy sources 5.2.2.2 - Steady State Voltage and Current conditions Parameter Supply Voltage Location (e.g. circuit designation) Test conditions Parameter 1 240Vac USB port Normal 5Vdc - 2 240Vac input circuit Normal 5Vdc - 2 240Vac input circuit Normal 240Vrms - 2 240Vac input circuit Normal 240Vrms - 2 240Vac input circuit Normal 240Vrms - 2 240Vac input circuit Normal - - Single fault – SC/OC - - - - 2 240Vac input circuit Normal - - 3 Single fault – SC/OC - - - -	Parameters		E 9					
No.	Volta	ige	circuit designation)	Test conditions	U (Vrms or Vpk)	l (Apk or Arms)	Hz	Class
1	240Vac		USB port	Normal	5Vdc	-	-	
				Abnormal	5Vdc	-	-	ES1
				Single fault – SC/OC	0Vdc	-	-	
2	240Vac	;	input circuit	Normal	240Vrms	-	-	
				Abnormal	-	-	-	ES3
				Single fault – SC/OC	-	-	-	



ſ

Page 47 of 92

Report No. 180301431SHA-001

				IEC	62368-1							
Clau	lse		Requirer	ment + Test			Re	esult - Rer	nark		Ve	erdict
3	-		-	Normal	-		-			-		
				Abnormal	-		-			-		
				Single fault – SC/OC	-		-			-		
5.2.2.3	- Capa	acitance	e Limits									
	Supr	olv	Location (e.g.				Para	ameters				
No.	Volta	age	circuit designation)	Test conditions	Capa	acitanc	e, nF		Upk	(V)	ES	Class
-	-		-	Normal	-			-				
				Abnormal	-			-				
				Single fault – SC/OC	-			-				
5.2.2.4	- Sing	le Pulse	es	·								
	Sup	olv	Location (e.g.	T (197			Para	ameters				
NO.	Volta	age	circuit designation)	l est conditions	Duratio	n (ms)	U	pk (V)	Ip	ok (mA)	LS	Class
				Normal								
				Abnormal								
				Single fault – SC/OC								
5.2.2.5	- Repe	etitive P	ulses									
	Supply	v	Location (e.g.	_			Para	meters				•
No.	Voltag	je	circuit designation)	l est conditions	Off time	(ms)	Up	k (V)	lpł	k (mA)	ES	Class
				Normal								
				Abnormal								
				Single fault – SC/OC								
Test C	onditio	ns:		·								
		Norr	mal –									
Supple	monto	Abn ny inform	ormal -	t Circuit OC-Shar	t Circuit							
Supple	menta	iy intoff	nation. 30=300									

Total Quality. Assured.

Page 48 of 92

Report No. 180301431SHA-001

Clause		Require	ment + Tes	st		R	esult - Re	emark		Verc
5.4.1.4, (9.0, B.2.	6.3.2, 6	TABLE: Temper	rature mea	surement	S				P)
		Supply voltage (V)	:	90	264	90	264		_
		Ambient T _{min} (°C)	:	40.0	40.0	25.0	25.0		_
		Ambient T _{max} (°C)	:	40.0	40.0	25.0	25.0		_
		Tma (°C)		:	40.0	40.0	40.0	40.0		_
		Model		:	GTM	36100-10	05-W2E-	USB		_
Maximur	n meas	sured temperature	e T of part/a	at:		T (°	C)		Allowe (°C	d T _{max} C)
1.Enclos	ure Ins	ide near Inlet Bla	de				49.3	42.9	75	5
2. PWB	near Re	ectifier Bridge (BI	D1)		91.3	80.5			13	0
3.Choke	(L1) Co	oil			87.2	78.0			11	0
4. Capac	citor (C	C1) body near Transform 85.5 76.9 — —					105			
5. Capac	citor (C2	2) body near Trar	nsform		89.3	81.4			105	
6. PWB I	near ne	ar Q1			103.0	94.6	3		13	0
7.Transf	ormer (T1) Primary Wind	ding		105.2	102.4			11	0*
8.Transf	ormer (T1) Secondary W	/inding		103.8	99.7			11	0*
9.Transf	ormer (T1) Core			98.9	94.3			Re	ef.
10.CY1 k	body ne	ear Transformer			85.0	81.0			12	25
11.CY2	body ne	ear Transformer			81.0	78.5			12	25
12.Capa	citor (C	7) body			76.9	75.8			10	5
13.Capa	citor (C	8) body			97.9	92.8			10	5
14.Enclo	sure In	side near Transfo	ormer (T1)	Тор	_		55.9	53.8	7	5
15.Enclo	sure O	utside near Trans	sformer (T1	I) Тор	_		52.7	50.4	7	5
Supplem limit valu	nentary le reduc	information: * inc ced 10K.	licated ther	mocouple	method v	vas used	to measu	ire the v	winding, s	o the
Tempera	ature T	of winding:	t1 (°C)	R1 (Ω)	t ₂ (°C)	R ₂ (Ω)	T (°(C)	Allowe d T _{max} (°C)	Insu tion clas
-			-	-	-	-	-		-	-

Total Quality. Assured.

Page 49 of 92

Report No. 180301431SHA-001

lause	Requirement	t + Test		Result - Remark				Ver
	TABLE: Temperature n	neasuremer	its					5
	Supply voltage (V)		90	264	90	264		_
	Ambient T _{min} (°C)	:	40.0) 40.0) 25.0	25.0) _	_
Ambient T _{max} (°C):) 40.0) 25.0	25.0) –	_
	Tma (°C)	:	40.0) 40.0	40.0	40.0) –	_
	Model	:		GTM86	5100-1005	-W2A	_	_
Maximu	m measured temperature T o	of part/at	:		T (°C)		Allowe (°	ed T _{ma} C)
1.Enclos	sure Inside near Inlet Blade		_	_	49.7	38.9) 7	'5
2. PWB	near Rectifier Bridge (BD1)		87.8	3 64.6	; _		1:	30
3.Choke	(L1) Coil		99.1	l 68.4	·		1	10
4. Capa	citor (C1) body near Transfor	rm	84.3	3 66.3	3		1(05
5. Capa	citor (C2) body near Transfor	rm	91.5	5 79.8	3		1(05
6. Trans	former (T1) Primary Winding	1	91.2	2 86.2	2		11	0*
7.Transf	ormer (T1) Secondary Windi	ing	92.1	I 91.4	·		11	0*
8.Transf	ormer (T1) Core		92.0) 86.5	5 —			ef.
9.CY1 b	ody near Transformer		80.7	7 76.3	3 —			25
10.CY2	body near Transformer		69.0) 67.3	3		1:	25
11.Capa	citor (C7) body		80.1	1 79.3	3 —		1(05
12.Capa	icitor (C8) body		67.2	2 66.4	· _		1(05
13.Enclo	osure Inside near Transforme	er (T1) Top			46.9	44.5	5 7	5
14.Enclo	osure Outside near Transform	mer (T1) Top	_		46.1	44.2	2 7	5
15.Outp	ut Cord		59.2	2 58.1			8	0
16. MOV1 near PCB				6 72.4	• _	_	1:	30
Supplem limit valu	nentary information:* indicate le reduced 10K.	d thermocou	ple metho	od was u	sed to me	asure the	winding, so	o the
Tempera	ature T of winding:	t ₁ (°C)	R ₁ (Ω)	t ₂ (°C)	R ₂ (Ω)	T (°C)	Allowed T _{max} (°C)	Insul tion class
-		-	-	-	-	-	-	-

Total Quality. Assured.

Page 50 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause	F	Requirement + Test		Result - Re	Verdict			
5.4.1.10.3	TABLE: Ball pre	ABLE: Ball pressure test of thermoplastics						
Allowed imp	ression diameter	(mm):	≤ 2 mm					
Object/Part I	No./Material	Manufacturer/trademark	Te	st temperature (°C)	Impression dia	meter (mm)		
Plu	g holder	1)		125	1.2	2		
Supplementary information:								
1) Refe	er to table 4.1.2							

5.4.2.2, 5.4.2.4 and 5.4.3 TABLE: Minin	mum (Clearance	s/Creepage	distance			Р
Clearance (cl) and creepage distance (cr) at/of/between:	Up (V)	U r.m.s. (V)	Frequency (kHz) ¹	Required cl (mm)	cl (mm) ²	Required ³ cr (mm)	cr (mm)
Model: GTM86100-1005-W2E-USB							
L to N before fuse(FI)	340	240	60Hz	2.3 ⁴	Min.4.0	2.4	Min.4.0
Two poles of fuse(FI)	340	240	60Hz	2.3 ⁴	Min.3.0	2.4	Min.3.0
CY1 Primary Pin to another Pin(BI)	340	240	60Hz	2.3 ⁴	3.9	2.4	3.9
CY2 Secondary Pin to another Pin(SI)	340	240	60Hz	2.3 ⁴	4.2	2.4	4.2
Live parts to Enclosure parts(RI)	396	272	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Live parts to accessible parts(RI)	396	272	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Primary circuit to secondary circuits (PCB trace under T1) (RI)	412	273	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Transformer Primary winding to secondary winding(RI)	412	273	60Hz	4.54	Min.7.0	5.5 ⁵	Min.7.0
Transformer Primary winding to core(RI)	412	273	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Model: GTM86100-1005-W2A							
L to N before fuse(FI)	340	240	60Hz	2.34	Min.4.0	2.4	Min.4.0
Two poles of fuse(FI)	340	240	60Hz	2.3 ⁴	Min.3.0	2.4	Min.3.0
CY1 Primary Pin to another Pin(BI)	340	240	60Hz	2.3 ⁴	3.9	2.4	3.9
CY2 Secondary Pin to another Pin(SI)	340	240	60Hz	2.3 ⁴	4.2	2.4	4.2
Live parts to Enclosure parts(RI)	400	274	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Live parts to accessible parts(RI)	400	274	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Primary circuit to secondary circuits (PCB trace under T1) (RI)		276	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Transformer Primary winding to secondary winding(RI)	420	276	60Hz	4.54	Min.7.0	5.5 ⁵	Min.7.0
Transformer Primary winding to core(RI)	420	276	60Hz	4.5 ⁴	Min.7.0	5.5 ⁵	Min.7.0
Supplementary information:			•				

Note 1: Only for frequency above 30 kHz Note 2: See table 5.4.2.4 if this is based on electric strength test



Page 51 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause	Requirement + Test	Result - Remark	Verdict
--------	--------------------	-----------------	---------

Note 3: Provide Material Group

Note 4: Required value was multiplied by the factor 1.48 due to the maximum specified altitude of 5000m

Note 5: Required creepage not less than required clearance

Note 6: Minimum 0.4 mm thick Mylar sheet or two layers of insulating tape wrap around internal conductive parts along the enclosure joint. This method is applied only to the model sold to high elevation region. Otherwise, the clearance and creepage distance is measured as 5.7/5.7 mm.

Note 7: Two layers of insulating tape or two layers of insulating tube wrap around the heatsink

5.4.4.2, 5.4.4.5 c) 5.4.4.9	TABLE: Distance	ce through ins	ulation meas	urements	5	Р
Distance through insulation	n di at/of:	Peak voltage (V)	Frequency (kHz)	Material	Required DTI (mm)	DTI (mm)
Model: GTM86100-1005-W	/2E-USB					
T1 transformer bobbin (RI)		412	60Hz	1)	0.4	0.6
Insulating tapes in transform	mer T1 (RI)	412	60Hz	1)	2 layers	2 layers
Thin sheet material at/of:	Peak voltage (V)	Frequency (kHz)	Material	Required DTI (mm)	DTI (mm)	
Insulation tape around tran	sformer	412	60Hz	1)	2 layers	2 layers
Model: GTM86100-1005-W	/2A					
Distance through insulation	n di at/of:	Peak voltage (V)	Frequency (kHz)	Material	Required DTI (mm)	DTI (mm)
T1 transformer bobbin (RI)		420	60Hz	1)	0.4	0.6
Insulating tapes in transform	mer T1 (RI)	420	60Hz	1)	2 layers	2 layers
Thin sheet material at/of:	Peak voltage (V)	Frequency (kHz)	Material	Required DTI (mm)	DTI (mm)	
Insulation tape around tran	420	60Hz	1)	2 layers	2 layers	
Supplementary information: 1) Refer to table 4.1.2	2					

5.4.9	TABLE: Electric strength tests	Р
-------	--------------------------------	---

Total Quality. Assured.

Page 52 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause	Requirement + Test	Result - Remark			Verdict	
Test voltag	ge applied between:	Voltage (AC, I	oltage shape (AC, DC)		V) B	reakdown Yes / No
GTM86100	0-1005-W2E-USB, GTM86100-1005-W2	2A				
Primary ci	rcuit to body (RI)	AC	;	4000Vp		No
Primary ci	rcuit to secondary circuit (RI)	AC		4000Vp		No
Primary wi	nding to secondary winding of T1 (RI)	AC		4000Vp		No
Primary wi	inding to core (RI)	AC		4000Vp		No
Insulation	tape around transformer per layer (RI)	AC	;	4000Vp		No
Insulation	sheet (BI)	AC		2600Vp		No
Primary ar	nd secondary of Y1 capacitor (RI)	DC	;	4000Vp		No
Suppleme	ntary information: N/A			•		

6.2.2	Table: Electrical	power sources	(PS) measurements for	or classification	Р	
Source	Description	Measurement	Max Power after 3 s	Max Power after 5 s*)	PS Classification	
	All circuits	Power (W) :	>100	>100		
А	exclude	V _A (V) :	-	-	PS3	
	USB port	I _A (A) :	-	-		
		Power (W) :	Max.9.8	Max.9.8		
В	USB port	V _A (V) :	-	-	PS1	
		I _A (A) :	-	-		
		Power (W) :	-	-		
С	-	V _A (V) :	-	-	-	
		I _A (A) :	-	-		
		Power (W) :	-	-		
D	-	V _A (V) :	-	-	-	
		I _A (A) :	-	-		
Supplementa	ary Information:					

(*) Measurement taken only when limits at 3 seconds exceed PS1 limits

6.2.3.2	Table: Determination of Potential Ignition Sources (Resistive PIS)	Р
---------	--	---



Page 53 of 92

Report No. 180301431SHA-001

IEC 62368-1

Clause		Requirement + Test		Resul	Verdict	
Circuit Loc	cation (x-y)	Operating Condition (Normal / Describe Single Fault)	Measured wattage or VA During first 30 s (W / VA)	Measured wattage or VA After 30 s (W / VA)	Protective Circuit, Regulator, or PTC Operated? Yes / No (Comment)	Resistive PIS? Yes/No
input Normal		Normal	13.9W	13.9W	No	Yes

Supplementary Information:

A combination of voltmeter, VA and ammeter IA may be used instead of a wattmeter.

If a separate voltmeter and ammeter are used, the product of (VA x IA) is used to determine Resistive PIS classification.

A Resistive PIS: (a) dissipates more than 15 W, measured after 30 s of normal operation, <u>or</u> (b) under single fault conditions has either a power exceeding 100 W measured immediately after the introduction of the fault if electronic circuits, regulators or PTC devices are used, or has an available power exceeding 15 W measured 30 s after introduction of the fault.

B.2.5	TABLE: In	put test					Р			
U (V)	I (A)	Irated (A)	P (W)	Fuse No	Ifuse (A)	Condition/status	5			
Model: GTM86100-1005-W2E-USB										
90	0.248		13.5	F1	0.248	Max Normal Load, 50 Hz				
90	0.262		13.4	F1	0.262	Max Normal Load, 60 Hz				
100	0.227	0.3	13.4	F1	0.227	Max Normal Load, 50 Hz				
100	0.243	0.3	13.4	F1	0.243	Max Normal Load, 60 Hz				
240	0.126	0.3	13.6	F1	0.126	Max Normal Load, 50 Hz				
240	0.133	0.3	13.6	F1	0.133	Max Normal Load, 60 Hz				
264	0.120		13.9	F1	0.120	Max Normal Load, 50 Hz				
264	0.125		13.9	F1	0.125	Max Normal Load, 60 Hz				
Model: GTN	Model: GTM86100-1005.2-W2E-USB									

Total Quality. Assured.

Page 54 of 92

Report No. 180301431SHA-001

			I	EC 62368-1			
Clause		Requirem	nent + Test		ŀ	Result - Remark	Verdict
90	0.247		13.3	F1	0.247	Max Normal Load, 50 Hz	Z
90	0.251		13.4	F1	0.251	Max Normal Load, 60 H	Z
100	0.229	0.3	13.2	F1	0.229	Max Normal Load, 50 H	Z
100	0.231	0.3	13.3	F1	0.231	Max Normal Load, 60 H	Z
240	0.126	0.3	13.4	F1	0.126	Max Normal Load, 50 H	Z
240	0.128	0.3	13.7	F1	0.128	Max Normal Load, 60 H	Z
264	0.118		13.6	F1	0.118	Max Normal Load, 50 H	Z
264	0.120		13.8	F1	0.125	Max Normal Load, 60 H	Z
Model: GT	M86100-1005	5-W2A	•				
90	0.244		13.5	F1	0.244	Max Normal Load, 50 H	Z
90	0.244		13.5	F1	0.244	Max Normal Load, 60 H	Z
100	0.220	0.3	13.5	F1	0.220	Max Normal Load, 50 H	Z
100	0.222	0.3	13.4	F1	0.222	Max Normal Load, 60 H	Z
240	0.122	0.3	13.8	F1	0.122	Max Normal Load, 50 H	Z
240	0.120	0.3	13.5	F1	0.120	Max Normal Load, 60 H	Z
264	0.116		13.6	F1	0.116	Max Normal Load, 50 H	Z
264	0.114		14.0	F1	0.114	Max Normal Load, 60 H	Z
Model: GT	M86100-1005	5.2-W2A	•				
90	0.243		13.6	F1	0.243	Max Normal Load, 50 H	Z
90	0.246		13.6	F1	0.246	Max Normal Load, 60 H	Z
100	0.219	0.3	13.4	F1	0.219	Max Normal Load, 50 H	Z
100	0.225	0.3	13.4	F1	0.225	Max Normal Load, 60 H	Z
240	0.123	0.3	13.6	F1	0.123	Max Normal Load, 50 H	Z
240	0.122	0.3	13.5	F1	0.122	Max Normal Load, 60 H	Z
264	0.114		14.0	F1	0.114	Max Normal Load, 50 H	Z
264	0.116		13.7	F1	0.116	Max Normal Load, 60 H	Z
Supplemer	ntary informat	ion:	•		•	-	

Total Quality. Assured.

Page 55 of 92

Report No. 180301431SHA-001

Clause		Requirement + Test Result - Remark					Verdict		
B.3	TABLE: Ab	normal c	perat	ing tes	ts				Р
Ambient ten	mbient temperature (°C): 22-25, if no else specified								
Power source	Power source for EUT: Manufacturer, model/type, output rating .: YOKOGAWA, WT310, 600VAC,20A								
Component No.	Abnormal Condition	Supply voltage (V)	Test time (ms)	Fuse no.	Fuse current (A)	T- couple	Temp. (°C)	Observation	า
GTM86100-	1005-W2E-L	JSB							
C1	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened imr no hazard	nediately
C2	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened imr no hazard	nediately
R6	Sc	264	2h	F1	0.121	-	-	Unit work normally r	o hazard
R3	Sc	264	1h	F1	0.02	-	-	Unit shutdown imme recoverable no haza	ediately Ird
D5	Sc	264	2h	F1	0.121	-	-	Unit work normally r	o hazard
D6	Sc	264	1h	F1	0.02	-	-	Unit shutdown imme recoverable no haza	ediately ard
R4	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened imr no hazard	nediately
R11	Sc	264	1h	F1	0.02	-	-	Unit shutdown imme recoverable no haza	ediately ard
R13	Sc	264	2h	F1	0.121	-	-	Unit work normally r	o hazard
T1 pin1-2	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened imr no hazard	nediately
T1 pin6-7	Sc	264	1h	F1	0.03	-	-	Unit shutdown imme recoverable no haza	ediately ard
R16	Sc	264	1h	F1	0.02	-	-	Unit shutdown imme recoverable no haza	ediately ard
D8	Sc	264	1h	F1	0.02	-	-	Unit shutdown imme recoverable no haza	ediately ard
C9	Sc	264	2h	F1	0.121	-	-	Unit work normally r	o hazard
Output	OI	264	2h			К	T1 winding: 130°C, Ta: 23°C	Max. output current: hazard	2.4A. no
GTM86100-	1005-W2A	•		•					
C1	Sc	264	1s	F1	>10→0	К	-	Fuse F1 opened imr no hazard	nediately

Page 56 of 92

Report No. 180301431SHA-001

,
•

Total Quality. Assured.

IEC 62368-1

Clause		Require	ment +	- Test			Resul	lt - Remark Verd		
C2	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened im no hazard	mediately	
R6	Sc	264	2h	F1	0.114	-	-	Unit work normally	no hazard	
R3	Sc	264	1h	F1	0.02	-	-	Unit shutdown imm recoverable no haz	ediately ard	
D1	Sc	264	2h	F1	0.114	-	-	Unit work normally	no hazard	
R8	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened im no hazard	mediately	
R9	Sc	264	1h	F1	0.02	-	-	Unit shutdown imm recoverable no haza	ediately ard	
T1 pin 1-2	Sc	264	1s	F1	>10→0	-	-	Fuse F1 opened im no hazard	mediately	
T1 pin A-B	Sc	264	1h	F1	0.03	-	-	Unit shutdown imm recoverable no haza	ediately ard	
R12	Sc	264	1h	F1	0.02	-	-	Unit shutdown imm recoverable no haza	ediately ard	
Output	OI	264	2h			К	T1 winding: 125.5°C, Ta: 23°C	Max. output current hazard	: 2.4A. no	

circuited test; "Uoc" means output voltage without load.

Annex Q.1	TABLE: Circuits intended for interconnection with building wiring (LPS)							
Note: Measured UOC (V) with all load circuits disconnected:								
Model: GTN	Model: GTM86100-1005-W2E-USB							
Output	Components	U _{oc} (V)	I _{sc}	(A)	Ś	S (VA)		
Circuit			Meas.	Limit	Meas.	Limit		
USB port	Normal condition	5.1	2.4	\leq 8.0 A	9.8	\leq 100 VA		
USB port	USB portSingle fault condition (R4 Short circuit)0 $\leq 8.0 \text{ A}$ 0 $\leq 100 \text{ VA}$							
Supplement SC=Short ci	Supplementary Information: SC=Short circuit. OC=Open circuit							

T.2, T.3, T.4, T.5	TABLE: Steady force test							
Part/Location	Material	Thickness (mm)	Force (N)	Test Duration (sec)	Observ	ation		
Enclosure	Plastics	1.5	250	5	No haz	zard.		
Supplementary in	Supplementary information: N/A							



Page 57 of 92

Report No. 180301431SHA-001

Clause		Require	ment + Test	Result - Remark		Verdict		
T.7 TABLE: Drop tests P								
Part/Locati	on	Material	Thickness (mm)		Drop Height (mm)	Ob	servation	
Enclosur	re Plastics 1.5 1000 No hazard.							
Supplementa	Supplementary information:							

T.8	TABLE: Stress relief test							
Part/Locati	on	Material	Thickness (mm)	Oven Temperature (°C)	Duration (h)	O	oservation	
Enclosure	е	Plastics	1.5	70	7	N	o hazard.	

intertek Total Quality. Assured.

Page 58 of 92

Report No. 180301431SHA-001

	IEC62368_1B - ATTACHMENT							
Clause	Requirement + Test	Result - Remark	Verdict					

		ATTA	CHMENT T	O TEST REPO	ORT					
(Audio/v	IEC 62368-1 EUROPEAN GROUP DIFFERENCES AND NATIONAL DIFFERENCES (Audio/video, information and communication technology equipment - Part 1: Safety requirements)									
Differences according to: EN 62368-1:2014+A11:2017										
Attachment Form No EU_GD_IEC62368_1B_II										
Attachment C	Attachment Originator: Nemko AS									
Master Attack	hment	: Da	te 2017-09-	22						
Copyright © 2 (IECEE), Gen	2017 IEC Syst eva, Switzerla	em for Confo and. All rights	rmity Testir reserved.	ng and Certific	cation of Elec	trical Equipmer	nt			
	CENELEC C		DIFICATION	IS (EN)			Р			
	Clauses, sub those in IEC	clauses, notes 62368-1:2014	, tables, figu are prefixed	res and annexe "Z".	es which are ad	dditional to				
CONTENTS	Add the following annexes: Annex ZA (normative) Normative references to international publications with their corresponding European publications Annex ZB (normative) Special national conditions Annex ZC (informative) A-deviations Annex ZD (informative) IEC and CENELEC code designations for flexible									
	Delete all the according to	e "country" note the following lis	s in the refe st:	rence documer	nt (IEC 62368-	1:2014)	Р			
	0.2.1	Note	1	Note 3	4.1.15	Note				
	4.7.3	Note 1 and 2	5.2.2.2	Note	5.4.2.3.2.2 Table 13	Note c				
	5.4.2.3.2.4	Note 1 and 3	5.4.2.5	Note 2	5.4.5.1	Note				
	5.5.2.1	Note	5.5.6	Note	5.6.4.2.1	Note 2 and 3				
	5.7.5	Note	5.7.6.1	Note 1 and 2	10.2.1 Table 39	Note 2, 3 and 4				
	10.5.3	Note 2	10.6.2.1	Note 3	F.3.3.6	Note 3				
	For special n	ational condition	ons, see An	nex ZB.			Р			
1	Add the follo NOTE Z1 The u electronic equipr 2011/65/EU.	wing note: use of certain subst ment is restricted w	ances in electri rithin the EU: se	ical and ee Directive			Р			

Total Quality. Assured.

Page 59 of 92

Clause	Requirement + Test	Result - Remark	Verdict
4.Z1	Add the following new subclause after 4.9: To protect against excessive current, short-circuits		N/A
	and earth faults in circuits connected to an a.c. mains , protective devices shall be included either as integral parts of the equipment or as parts of the building installation, subject to the following, a), b) and c):		
	a) except as detailed in b) and c), protective devices necessary to comply with the requirements of B.3.1 and B.4 shall be included as parts of the equipment;		
	b) for components in series with the mains input to the equipment such as the supply cord, appliance coupler, r.f.i. filter and switch, short-circuit and earth fault protection may be provided by protective devices in the building installation;		
	c) it is permitted for pluggable equipment type B or permanently connected equipment , to rely on dedicated overcurrent and short-circuit protection in the building installation, provided that the means of protection, e.g. fuses or circuit breakers, is fully specified in the installation instructions.		
	If reliance is placed on protection in the building installation, the installation instructions shall so state, except that for pluggable equipment type A the building installation shall be regarded as providing protection in accordance with the rating of the wall socket outlet.		
5.4.2.3.2.4	Add the following to the end of this subclause:		N/A
	The requirement for interconnection with external circuit is in addition given in EN 50491-3:2009.		
10.2.1	Add the following to ^{c)} and ^{d)} in table 39: For additional requirements, see 10.5.1.		Р

Total Quality. Assured.

Page 60 of 92

Clause	Requirement + Test	Result - Remark	Verdict
		I	
10.5.1	Add the following after the first paragraph: For RS 1 compliance is checked by measurement under the following conditions:		N/A
	In addition to the normal operating conditions, all controls adjustable from the outside by hand, by any object such as a tool or a coin, and those internal adjustments or presets which are not locked in a reliable manner, are adjusted so as to give maximum radiation whilst maintaining an intelligible picture for 1 h, at the end of which the measurement is made. NOTE Z1 Soldered joints and paint lockings are examples of adequate locking.		
	The dose-rate is determined by means of a radiation monitor with an effective area of 10 cm ² , at any point 10 cm from the outer surface of the apparatus.		
	Moreover, the measurement shall be made under fault conditions causing an increase of the high- voltage, provided an intelligible picture is maintained for 1 h, at the end of which the measurement is made.		
	For RS1, the dose-rate shall not exceed 1 µSv/h taking account of the background level. NOTE Z2 These values appear in Directive 96/29/Euratom of 13		
10.6.1	May 1996. Add the following paragraph to the end of the		Р
	EN 71-1:2011, 4.20 and the related tests methods and measurement distances apply.		
10.Z1	Add the following new subclause after 10.6.5. 10.Z1 Non-ionizing radiation from radio frequencies in the range 0 to 300 GHz		Р
	The amount of non-ionizing radiation is regulated by European Council Recommendation 1999/519/EC of 12 July 1999 on the limitation of exposure of the general public to electromagnetic fields (0 Hz to 300 GHz).		
	For intentional radiators, ICNIRP guidelines should be taken into account for Limiting Exposure to Time-Varying Electric, Magnetic, and Electromagnetic Fields (up to 300 GHz). For hand- held and body-mounted devices, attention is drawn to EN 50360 and EN 50566		
G.7.1	Add the following note: NOTE Z1 The harmonized code designations corresponding to the IEC cord types are given in Annex ZD.		N/A

Total Quality. Assured.

Page 61 of 92

Clause	Requirement + Te	est		Result - Remark	Verdict			
Bibliography	Add the following	standards:			Ν/Δ			
Dibilography	Add the following others for the standards indicated:							
	IEC 60130-9	NOTE Harmonized as EN	60130	-9				
	IEC 60269-2	NOTE Harmonized as HD	60269	-9. -2				
	IEC 60309-1	NOTE Harmonized as FN	60200	, <u>2</u> .				
	IEC 60364	NOTE some parts harmon	ized in	HD 384/HD 60364 series				
	IEC 60601-2-4 NOTE Harmonized as EN 60601-2-4							
	IEC 60664-5	NOTE Harmonized as EN	60664-	-5				
	IEC 61032-1997	NOTE Harmonized as EN	61032 [.]	1998 (not modified)				
	IEC 61508-1	NOTE Harmonized as EN	61508-	-1				
	IEC 61558-2-1	NOTE Harmonized as EN	61558-	-2-1				
	IEC 61558-2-4	NOTE Harmonized as EN	61558-	-2-4				
	IEC 61558-2-6	NOTE Harmonized as EN	61558-	-2-6				
	IEC 61643-1	NOTE Harmonized as EN	61643-	-1				
	IEC 61643-21 NOTE Harmonized as EN 61643-21							
	IEC 61643-311 NOTE Harmonized as EN 61643-311							
	IEC 61643-321 NOTE Harmonized as EN 61643-321							
	IEC 61643-331 NOTE Harmonized as EN 61643-331.							
70					N/A			
20	Denmark Finland Nerway and Sweden							
4.1.15	Denmark, Finland, Norway and Sweden							
	To the end of the subclause the following is added:							
	connection to othe	e equipment type A intende er equipment or a network sh	all, if					
	safety relies on co	onnection to reliable earthing	or if					
	surge suppressor	s are connected between the						
	network terminals and accessible parts, have a marking stating that the equipment shall be							
	connected to an e	connected to an earthed mains socket-outlet.						
	The marking text	The marking text in the applicable countries shall be						
	as follows:							
	In Denmark : "App	paratets stikprop skal tilslutte	s en					
	stikkontakt med jo	ord som giver forbindelse til "						
	In Finland : "Laite	on liitettävä suojakoskettimil	а					
	In Norway : "Appa	rasiaan" iratet må tilkoples jordet						
	stikkontakt"	stikkontakt"						
	In Sweden : "Appa uttag"	araten skall anslutas till jorda	t					
4.7.3	United Kingdom				N/A			
	To the end of the	subclause the following is ad	ded:					
	The torque test is performed using a socket-outlet complying with BS 1363, and the plug part shall be assessed to the relevant clauses of BS 1363. Also see Annex G.4.2 of this annex							

Total Quality. Assured.

Clause	Requirement + Test	Result - Remark	Verdict
5.2.2.2	Denmark		N/A
	After the 2nd paragraph add the following: A warning (marking safeguard) for high touch current is required if the touch current exceeds the limits of 3,5 mA a.c. or 10 mA d.c.		
5.4.11.1 and	Finland and Sweden		N/A
Annex G	To the end of the subclause the following is added:		
	For separation of the telecommunication network from earth the following is applicable:		
	If this insulation is solid, including insulation forming part of a component, it shall at least consist of either		
	• two layers of thin sheet material, each of which shall pass the electric strength test below, or		
	• one layer having a distance through insulation of at least 0,4 mm, which shall pass the electric strength test below.		
	If this insulation forms part of a semiconductor component (e.g. an optocoupler), there is no distance through insulation requirement for the insulation consisting of an insulating compound completely filling the casing, so that clearances and creepage distances do not exist, if the component passes the electric strength test in accordance with the compliance clause below and in addition		
	• passes the tests and inspection criteria of 5.4.8 with an electric strength test of 1,5 kV multiplied by 1,6 (the electric strength test of 5.4.9 shall be performed using 1,5 kV), and		
	• is subject to routine testing for electric strength during manufacturing, using a test voltage of 1,5kV.		
	It is permitted to bridge this insulation with a capacitor complying with EN 60384-14:2005, subclass Y2.		
	A capacitor classified Y3 according to EN 60384- 14:2005, may bridge this insulation under the following conditions:		
	• the insulation requirements are satisfied by having a capacitor classified Y3 as defined by EN 60384- 14, which in addition to the Y3 testing, is tested with an impulse test of 2,5 kV defined in 5.4.11;		
	• the additional testing shall be performed on all the test specimens as described in EN 60384-14;		
	the impulse test of 2,5 kV is to be performed before the endurance test in EN 60384-14, in the sequence of tests as described in EN 60384-14.		
5.5.2.1	Norway		N/A
	After the 3rd paragraph the following is added:		
	Due to the IT power system used, capacitors are required to be rated for the applicable line-to-line voltage (230 V).		

Total Quality. Assured.

Page 63 of 92

Clause	Requirement + Test	Result - Remark	Verdict
			1
5.5.6	Finland, Norway and Sweden		N/A
	To the end of the subclause the following is added:		
	Resistors used as basic safeguard or bridging basic insulation in class I pluggable equipment type A shall comply with G.10.1 and the test of G.10.2.		
5.6.1	Denmark		N/A
	Add to the end of the subclause		
	Due to many existing installations where the socket- outlets can be protected with fuses with higher rating than the rating of the socket-outlets the protection for pluggable equipment type A shall be an integral part of the equipment. <i>Justification:</i> In Denmark an existing 13 A socket outlet can be protected by a 20 A fuse.		
5.6.4.2.1	Ireland and United Kingdom		N/A
	After the indent for pluggable equipment type A , the following is added:		
	 the protective current rating is taken to be 13 A, this being the largest rating of fuse used in the mains plug. 		
5.6.5.1	To the second paragraph the following is added:		N/A
	The range of conductor sizes of flexible cords to be accepted by terminals for equipment with a rated current over 10 A and up to and including 13 A is:		
5.7.5	Denmark		N/A
	To the end of the subclause the following is added:		
	The installation instruction shall be affixed to the equipment if the protective conductor current exceeds the limits of 3,5 mA a.c. or 10 mA d.c.		

Total Quality. Assured.

Clause	Requirement + Test	Result - Remark	Verdict
5.7.6.1	Norway and Sweden		N/A
	To the end of the subclause the following is added:		
	The screen of the television distribution system is normally not earthed at the entrance of the building and there is normally no equipotential bonding system within the building. Therefore the protective earthing of the building installation needs to be isolated from the screen of a cable distribution system.		
	It is however accepted to provide the insulation external to the equipment by an adapter or an interconnection cable with galvanic isolator, which may be provided by a retailer, for example.		
	The user manual shall then have the following or similar information in Norwegian and Swedish language respectively, depending on in what country the equipment is intended to be used in:		
	 "Apparatus connected to the protective earthing of the building installation through the mains connection or through other apparatus with a connection to protective earthing – and to a television distribution system using coaxial cable, may in some circumstances create a fire hazard. Connection to a television distribution system therefore has to be provided through a device providing electrical isolation below a certain frequency range (galvanic isolator, see EN 60728-11)" NOTE In Norway, due to regulation for CATV-installations, and in Sweden, a galvanic isolator shall provide electrical insulation below 5 MHz. The insulation shall withstand a dielectric strength of 1,5 kV r.m.s., 50 Hz or 60 Hz, for 1 min. Translation to Norwegian (the Swedish text will also be accepted in Norway): "Apparater som er koplet til beskyttelsesjord via nettplugg og/eller via annet jordtilkoplet utstyr – og er tilkoplet et koaksialbasert kabel-TV nett, kan forårsake brannfare. For å unngå dette skal det ved tilkopling av apparater til kabel-TV nett 		
	og kabel-TV nettet." Translation to Swedish:		
	"Apparater som är kopplad till skyddsjord via jordat vägguttag och/eller via annan utrustning och samtidigt är kopplad till kabel-TV nät kan i vissa fall medfőra risk főr brand. Főr att undvika detta skall vid anslutning av apparaten till kabel-TV nät galvanisk isolator finnas mellan apparaten och kabel-TV nätet.".		

Total Quality. Assured.

Page 65 of 92

Clause	Requirement + Test	Result - Remark	Verdict
5.7.6.2	Denmark To the end of the subclause the following is added: The warning (marking safeguard) for high touch current is required if the touch current or the protective current exceed the limits of 3,5 mA.		N/A
B.3.1 and B.4	Ireland and United Kingdom The following is applicable: To protect against excessive currents and short- circuits in the primary circuit of direct plug-in equipment , tests according to Annexes B.3.1 and B.4 shall be conducted using an external miniature circuit breaker complying with EN 60898-1, Type B, rated 32A. If the equipment does not pass these tests, suitable protective devices shall be included as an integral part of the direct plug-in equipment , until the requirements of Annexes B.3.1 and B.4 are met		N/A
G.4.2	 Denmark To the end of the subclause the following is added: Supply cords of single phase appliances having a rated current not exceeding 13 A shall be provided with a plug according to DS 60884-2-D1:2011. CLASS I EQUIPMENT provided with socket-outlets with earth contacts or which are intended to be used in locations where protection against indirect contact is required according to the wiring rules shall be provided with a plug in accordance with standard sheet DK 2-1a or DK 2-5a. If a single-phase equipment having a RATED CURRENT exceeding 13 A or if a poly-phase equipment is provided with a supply cord with a plug, this plug shall be in accordance with the standard sheets DK 6-1a in DS 60884-2-D1 or EN 60309-2. Mains socket outlets intended for providing power to Class II apparatus with a rated current of 2,5 A shall be in accordance DS 60884-2-D1:2011 standard sheet DKA 1-4a. Other current rating socket outlets shall be in compliance with Standard Sheet DKA 1-3a or DKA 1-1c. Mains socket-outlets with earth shall be in compliance with DS 60884-2-D1:2011 Standard Sheet DK 1-3a, DK 1-1c, DK1-1d, DK 1-5a or DK 1-7a <i>Justification:</i> Heavy Current Regulations, Section 6c		N/A

Total Quality. Assured.

Page 66 of 92

Clause	Requirement + Test	Result - Remark	Verdict
G.4.2	United Kingdom To the end of the subclause the following is added: The plug part of direct plug-in equipment shall be assessed to BS 1363: Part 1, 12.1, 12.2, 12.3, 12.9, 12.11, 12.12, 12.13, 12.16, and 12.17, except that the test of 12.17 is performed at not less than 125 °C. Where the metal earth pin is replaced by an Insulated Shutter Opening Device (ISOD), the requirements of clauses 22.2 and 23 also apply.		N/A
G.7.1	United Kingdom To the first paragraph the following is added: Equipment which is fitted with a flexible cable or cord and is designed to be connected to a mains socket conforming to BS 1363 by means of that flexible cable or cord shall be fitted with a 'standard plug' in accordance with the Plugs and Sockets etc (Safety) Regulations 1994, Statutory Instrument 1994 No. 1768, unless exempted by those regulations. NOTE "Standard plug" is defined in SI 1768:1994 and essentially means an approved plug conforming to BS 1363 or an approved conversion plug.		N/A
G.7.1	Ireland To the first paragraph the following is added: Apparatus which is fitted with a flexible cable or cord shall be provided with a plug in accordance with Statutory Instrument 525: 1997, "13 A Plugs and Conversion Adapters for Domestic Use Regulations: 1997. S.I. 525 provides for the recognition of a standard of another Member State which is equivalent to the relevant Irish Standard		N/A
G.7.2	Ireland and United Kingdom To the first paragraph the following is added: A power supply cord with a conductor of 1,25 mm ² is allowed for equipment which is rated over 10 A and up to and including 13 A.		N/A

Total Quality. Assured.

Page 67 of 92

Clause	Requirement + Test	Result - Remark	Verdict
70			NI/A
20	ANNEX ZC, NATIONAL DEVIATIONS (EN)		N/A
10.5.2	Germany		N/A
	The following requirement applies:		
	For the operation of any cathode ray tube intended for the display of visual images operating at an acceleration voltage exceeding 40 kV, authorization is required, or application of type approval (Bauartzulassung) and marking.		
	Justification: German ministerial decree against ionizing radiation (Röntgenverordnung), in force since 2002-07-01, implementing the European Directive 96/29/EURATOM.		
	NOTE Contact address: Physikalisch-Technische Bundesanstalt, Bundesallee 100, D-38116 Braunschweig, Tel.: Int +49-531-592-6320, Internet: http://www.ptb.de		



Page 68 of 92

Report No. 180301431SHA-001

IEC62368_1B - ATTACHMENT

Clause

Requirement + Test

Result - Remark

ATTACHMENT TO TEST REPORT					
IEC 62368-1 (AUSTRALIA / NEW ZEALAND) NATIONAL DIFFERENCES (Audio/video, information and communication technology equipment)					
Differences	according to: AS/NZS 62368.1:2018				
Attachmen	t Form No : AU_NZ_ND_IEC62368_1B				
Attachmen	t Originator: JAS-ANZ				
Master Att	achment: 2018-02				
Copyright Geneva, S	© 2017 IEC System for Conformity Testing and Certification of Electrical Equipmen witzerland. All rights reserved.	ot (IECEE),			
	National Differences				
Appendix ZZ	Variations to IEC 62368-1:2014 (ED. 2.0) for Australia and New Zealand	-			
ZZ1 Scope	This Appendix lists the normative variations to IEC 62368-1:2014 (ED. 2.0)	-			
ZZ2 Variations	The following modifications are required for Australian/New Zealand conditions:	-			
2	Add the tollowing to the list of normative references: The following normative documents are referenced in Appendix ZZ: -AS/NZS 3112, Approval and test specification— Plugs and socket-outlets -AS/NZS 3123, Approval and test specification— Plugs, socket-outlets and couplers for general industrial application -AS/NZS 3191, Electric flexible cords -AS/NZS 60065, Audio, video and similar electronic apparatus—Safety requirements (IEC 60065:2015 (ED.8.0) MOD) -AS/NZS 60320.1, Appliance couplers for household and similar general purposes, Part 1: General requirements (IEC 60320-1, Ed.2.1 (2007) MOD) -AS/NZS 60320.2.2, Appliance couplers for household and similar general purposes Part 2.2: Interconnection couplers for household and similar equipment (IEC 60320-2- 2, Ed.2.0 (1998) MOD) -ASINZS 60695.2.11, Fire hazard testing, Part 2.11: Glowing/hot wire based test methods— Glow-wire flammability test method for end- products -ASINZS 60695.11.5, Fire hazard testing, Part 1.5: Test flames—Needle-flame test method— Apparatus, confirmatory test arrangement and	-			

Total Quality. Assured.

Page 69 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
	-AS/NZS 60695.11.10, Fire hazard testing, Part 11.10: Test flames—50 W horizontal and vertical flame test methods -AS/NZS 60884.1, Plugs and socket-outlets for household and similar purposes, Part 1: General requirements -AS/NZS 60950.1:2015, Information technology equipment—Safety, Part 1: General requirements (IEC 60950-1, Ed.2.2 (2013), MOD) IEC 61032:1997, Protection of persons and equipment by enclosures—Probes for verification -AS/NZS 61558.1:2008 (including Amendment 2:2015), Safety of Power Transformers, Power Supplies, Reactors and Similar Products, Part 1: General requirements and tests (IEC 61558-1 Ed 2.1, MOD) -AS/NZS 61558.2.16, Safety of transformers, reactors, power supply units and similar products for voltages up to 1 100 V, Part 2.16: Particular requirements and tests for switch mode power supply units and transformers for switch mode power supply units.		
4.1.1	 Application of requirements and acceptance of materials, components and subassemblies 1 Replace the text 'IEC 60950-1' with 'AS/NZS 60950.1:2015'. 2 Replace the text 'IEC 60065' with 'AS/NZS 60065'. 	F	P
4.7	Equipment for direct insertion into mains sock	et-outlets	N/A
4.7.2	Requirements Delete the text of the second paragraph and replace with the following: Equipment with a plug portion, suitable for insertion into a 10 A 3-pin flat-pin socket-outlet complying with AS/NZS 3112 shall comply with the requirements in AS/NZS 3112 for equipment with integral pins for insertion into socket-outlets. Compliance Criteria		N/A
4.7.3	Delete the first paragraph and Note 1 and Note 2 and replace with the following: Compliance is checked by inspection and, if necessary, by the tests in AS/NZS 3112.		N/A
4.8	Delete existing clause title and replace with the fol 4.8 Products containing coin/button cell batter	lowing: ies	N/A



Page 70 of 92

Report No. 180301431SHA-001

Clause Requirement + Test		Resu	lt - Remark		Verdict			
4.8.1	Gen 4 - ind of 32 2 A follo NOT 3 A exis 4 F	General 4 Second dashed point, delete the text and replace with the following: - include coin/button cell batteries with a diameter of 32 mm or less. 2 After the second dashed point, insert the following Note: NOTE 1: Batteries are specified in IEC 60086-2. 3 After the third dashed point, renumber the existing Note as 'NOTE 2'. 4 Fifth dashed point, delete the word 'lithium'.						N/A
4.8.2	Inst First	Instructional Safeguard					N/A	
4.8.3	Con First word coin	struction i line, after the ds 'containing /button batter	e word 'Equi one or more ries and'	oment' <i>insert</i> the				N/A
4.8.5	Compliance criteria Delete the first paragraph and replace with the following: Compliance is checked by applying a force of 30 N +/-1 N for 10 s to the battery compartment door/cover by a rigid test finger according to test probe 11 of IEC 61032:1997 at the most unfavourable place and in the most unfavourable direction. The force shall be applied in one				N/A			
5.4.10.2	Tes	t methods	-					N/A
5.4.10.2.1	General Delete the first paragraph and replace with the following: In Australia only, the separation is checked by the test of both Clause 5.4.10.2.2 and Clause 5.4.10.2.3. In New Zealand, the separation is checked by the test of either Clause					N/A		
Table 29	Rep	<i>lace</i> the tab	le with the	following:				N/A
Parts Parts indicated in		New Zealand 2.5 kV	Impulse test Australia 7.0 kV for hand-held telephones		Steady state New Zealand 1.5 kV	e test Austral ia 3 kV		
Parts indicated in 1.5 kV 10/700 µs ° 1.0 kV 1.5 kV Clause 5.4.10.1 b) and c) ° 1.5 kV 10/700 µs ° 1.0 kV 1.5 kV ° Surge suppressors shall not be removed. ° ° 1.0 kV 1.5 kV ° During this test, it is allowed for a surge suppressor to operate and for a sparkover to occur ° 0 0								

Total Quality. Assured.

Page 71 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test Result - Remark		Verdict	
5.4.10.2.2	After the first paragraph, <i>insert</i> new Notes 201 and 202 as follows: NOTE 201 For Australia, the 7 kV impulse simulates lightning surges on typical rural and semi-rural network lines. NOTE 202 For Australia, the value of 2.5 kV for Clause 5.4.10.1 a) was chosen to ensure the adequacy of the insulation concerned and does not necessarily simulate likely overvoltages			N/A
5.4.10.2.3	After the first paragraph, <i>insert</i> new Notes 201 and 202 as follows: NOTE 201 For Australia, where there are capacitors across the insulation under test, it is recommended that d.c. test voltages are used. NOTE 202 The 3 kV and 1.5 kV values for Australia have been determined considering the low frequency induced voltages from the power supply distribution system.			N/A
6	Electrically-caused fire			Р
6.1	General After the first paragraph, <i>insert</i> the following new paragraph: Alternatively, the requirements of Clauses 6.2 to 6.5.2 are considered to be fulfilled if the equipment complies with the requirements of Clause 6.202	,		Р
6.6	After Clause 6.6, <i>add</i> the new Clauses 6.201 and 6.201 External power supplies, docking static 6.202 Resistance to fire—Alternative tests (see special national conditions)	d 6.202 ons and	as follows: I other similar devices and	N/A
8.5.4	Special categories of equipment comprising	moving	j parts	N/A
8.5.4.1	Large data storage equipment In the first dashed row and the second dashed rows <i>replace</i> 'IEC 60950-1:2005' with 'AS/NZS 60950.1:2015'.			N/A
8.6	Stability of equipment			N/A



Page 72 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test	Result - Remark	Verdict
8.6.1 and Table 36	 Requirements Table 36, <i>insert</i> Footnote c at the end of the 'Glass slide' heading, and <i>add</i> a new Footnote c after the text of Footnote b in the last row of Table 36 as follows: The glass slide test is not applicable to floor standing equipment, even though the equipment may have controls or a display. Table 36, fifth row, <i>insert</i> '²⁰¹' at the end of 'No stability requirements' Table 36, ninth row, <i>insert</i> '²⁰¹' at the end of 'No stability requirements' Table 36, add the following new footnote: ²⁰¹ MS2 and MS3 television sets and display devices, designed only for fixing to a wall, ceiling or equipment rack, are not subjected to stability requirements of Clause 8.6.4 and horizontal force requirements of Clause 8.6.5 apply. Second paragraph beneath Table 36, <i>delete</i> the words 'MS2 and MS3 television sets and display devices itelevision sets and display devices itelevision sets and MS3 television sets and MS3 television sets and MS3 television sets 8.6.4 and horizontal force requirements of Clause 8.6.5 apply. 	e	N/A
8.6.1	After Clause 8.6.1 <i>add</i> the following new clauses: 8.6.1.201 Instructional safeguard for fixed- mount television sets (see special national conditions)		N/A
Annex F Paragraph F.3.5.1	Mains appliance outlet and socket-outlet markings Replace 'IEC 60320-2-2' with 'AS/NZS 60320.2.2'.		N/A
Annex G Paragraph G.4.2	Mains connectors 1 In the second line <i>insert</i> 'or AS/NZS 3123' after 'IEC 60906-1'. 2 In the second line <i>insert</i> 'or AS/NZS 60320 series' after 'IEC 60320 series' 3 <i>Add</i> the following new paragraph: 10 A or 15 A 250 V flat pin plugs for the connection of equipment to mains-powered socket-outlets for household or similar general uses shall comply with AS/NZS 3112 or AS/NZS 60884.1.	e	N/A
Paragraph G.5.3.1	Transformers, General 1 In the third dashed point <i>replace</i> 'IEC 61558-1 and the relevant parts of IEC 61558-2' with 'AS/NZS 61558-1 and the relevant parts of AS/NZS 61558.2' 2 In the fourth dashed point <i>replace</i> 'IEC 61558- 2-16' with 'AS/NZS 61558.2.16'.		N/A
Paragraph G.7.1	Mains supply cords, General In the fourth dashed paragraph, <i>replace</i> 'IEC 60320-1' with 'AS/NZS 60320.1'		

Total Quality. Assured.

Page 73 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test Result - Remark			Verdict	
Table G.5	Sizes of conductors 1 In the second row, first column, <i>delete</i> '6' and <i>replace</i> with '7.5' 2 In the second row, second column, <i>delete</i> '0,75' and <i>replace</i> with '0.75 ^b 3 <i>Delete</i> Note 1. 4 <i>Replace</i> 'NOTE 2' with 'NOTE:'. 5 <i>Delete</i> the text of 'Footnote b' and <i>replace</i> with the following: ^b This nominal cross-sectional area is only allowed for Class II appliances if the length of the power supply cord, measured between the point where the cord, or cord guard, enters the appliance, and the entry to the plug does not exceed 2 m (0.5 mm2 three-core supply flexible cords are not permitted; see AS/NZS 3191). 6 In Footnote c <i>replace</i> 'IEC 60320-1' with 'AS/NZS 60320.1' 7 In Footnote d <i>replace</i> 'IEC 60320-1' with				N/A
Annex M Paragraph M.3.2	Protection circuits for batteries provided within the equipment, Test method After the first dashed point <i>add</i> the following Note: NOTE 201: In cases where the voltage source is provided by power from an unassociated power source, consideration should be given to the effects of possible single fault conditions in the unassociated equipment. If the power source is unknown then it should be assumed that the maximum limit of SELV may be applied to the source input under assumed single fault conditions in the source when assessing the charging circuit in the equipment under test.				N/A
	Spe	ecial national conditions (if any)			N/A
intertek

Total Quality. Assured.

Page 74 of 92

Report No. 180301431SHA-001

Clause		Requirement + Test		Result - Remark	Verdict
6.201	Ext oth For oth and dur out – a incr rate con of it con for the con NO bat acc bat Con tak ope sim	ernal power supplies, docking stations and er similar devices external power supplies, docking stations and er similar devices, during after abnormal operating conditions and ing single fault conditions the put voltage— t all ES1 outlets or connectors shall not rease by more than 10% of its ed output voltage under normal operating dition; and f a USB outlet or connector shall not increase more than 3 V or 10% ts rated output voltage under normal operating ditions, whichever is higher. equipment with multiple rated output voltages, requirements apply with the equipment figured for each rated output voltage in turn. TE: This is intended to reduce the possibility of tery fire or explosion in attached equipment or ressories when charging secondary lithium teries. mpliance shall be checked by measurement, ing into account the abnormal erating conditions of Annex B.3 and the mulated single-fault conditions of Annex B.4			N/A
6.202	Re	sistance to fire—Alternative tests			N/A
6.202.1	Gen Parigni Thi trim or t a) (hav AS/ only con m b) 1 neg - si not can - si with inte pac acco NOT wha acco adja for t	heral ts of non-metallic material shall be resistant to tion and spread of fire. s requirement does not apply to decorative as, knobs and other parts unlikely to be ignited o propagate flames from inside the equipment, he following: Components that are contained in an enclosure ring a flammability category of V-0 according to (NZS 60695.11.10 and having openings y for the connecting wires filling the openings npletely, and for ventilation not exceeding 1 n in width regardless of length. The following parts which would contribute gligible fuel to a fire: mall mechanical parts, the mass of which does exceed 4 g, such as mounting parts, gears, ns, belts and bearings; mall electrical components, such as capacitors n a volume not exceeding 1 750 mm3, egrated circuits, transistors and optocoupler ckages, if these components are mounted on terial of flammability category V-1, or better, bording to AS/NZS 60695.11.10. TE: In considering how to minimize propagation of fire and t 'small parts' are, ount should be taken of the cumulative effect of small parts cent to each other he possible effect of propagating the fire from one part to her.	See	table 1.5.1	Ρ



Page 75 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test		Result - Remark	Verdict
	Compliance shall be che Clauses 6.202.2, 6.202 For the base material of compliance shall be che of Clause 6.202.5. The tests shall be carrier metallic material which h the equipment. When the out, the parts shall be pla orientation as they would These tests are not carri	ecked by the tests of 3 and 6.202.4. printed boards, cked by the test d out on parts of non- have been removed from e glow-wire test is carried aced in the same d be in normal use. ed out on internal wiring.		N/A
6.202.2	Testing of non-metallic Parts of non-metallic ma the glow-wire test of AS/ shall be carried out at 55 Parts for which the glow- carried out, such as thos material, shall meet the ISO 9772 for category F wire test shall be not car material classified at lea 9772 provided that the re than the sample tested.	c materials terial shall be subject to NZS 60695.2.11 which 50°C. wire test cannot be se made of soft or foamy requirements specified in H-3 material. The glow- ried out on parts of st FH-3 according to ISO elevant part is not thinner	Approved.	N/A
6.202.3	Testing of insulating materialsParts of insulating material supporting PotentialIgnition Sources shall be subjectto the glow-wire test of AS/NZS 60695.2.11 whichshall be carried out at 750°C.The test shall be also carried out on other parts ofinsulating material which arewithin a distance of 3 mm of the connection.NOTE: Contacts in components such as switch contacts are			N/A
	For parts which withstan produce a flame, other p within the envelope of a diameter of 20 mm and a subjected to the needle- However, parts shielded the needle-flame test ne	d the glow-wire test but arts above the connection vertical cylinder having a a height of 50 mm shall be flame test. by a barrier which meets ed not be tested		N/A
	accordance with AS/NZS following modifications: Clause of AS/NZS 60695.11.5	Change		
	9 Test procedure 9.2 Application of needle-flame	<i>Delete</i> the first and second paragraphs and <i>replace</i> with the following: The specimen shall be		N/A



Page 76 of 92

Report No. 180301431SHA-001

Clause	Requirement + Test		Result - Remark	Verdict
		flame can be applied to a vertical or horizontal edge as shown in the examples of Figure 1. If possible the flame shall be applied at least 10 mm from a corner. The duration of		
		application of the test flame shall be 30 s 1 s.		
	9.3 Number of test specimens	Replace with the following: The test shall be made on one specimen. If the specimen does not withstand the test, the test may be repeated on two further		
		specimens, both of which shall withstand the test.		
	11 Evaluation of test results	Replace with the following: The duration of burning (tb) shall not exceed 30 s. However, for printed circuit boards, it shall not		
	The needle-flame test shaparts of material classifier V-0 or V-1 according to A provided that the relevant the sample tested.	exceed 15 s. all not be carried out on d as S/NZS 60695.11.10, t part is not thinner than		
6.202.4	Testing in the event of material	non-extinguishing		
	If parts, other than enclose the glow wire tests of Cla extinguish within 30 s after glowwire tip, the needle-f Clause 6.202.3 shall be r metallic material which ar mm or which are likely to flame during the tests of a shielded by a separate ba needle-flame test need n NOTE 1: If the enclosure does the equipment is considered to requirements of Clause 6.202 w consequential testing.	sures, do not withstand use 6.202.3, by failure to er the removal of the lame test detailed in nade on all parts of non- re within a distance of 50 be impinged upon by Clause 6.202.3. Parts arrier which meets the ot be tested. not withstand the glow-wire test have failed to meet the vithout the need for		N/A



Page 77 of 92

Report No. 180301431SHA-001

Clause		Requirement + Test	 Result - Remark	 Verdict
Clause 6.202.5	NOT to ig or gl unde have the r NOT cons could have the n sub 6.2t the whe The con is le The con is le The con con the gn f the con con con the con con con the con con con the con con con the con con con the con con con the con con con the con con con con con the con con con the con con con con the con con con the con con con the con con con the con con the con con the con con the con con the con con the con con the con con the con con the con con the con con the con the con con the the con the the con the con the con the con the con the con the con the con the the the con the the con the con the the con the the con the con the the the the the the the the the the	Requirement + Test E 2: If other parts do not withstand the glow-wire test due nition of the tissue paper and if this indicates that burning owing particles can fall onto an external surface erneath the equipment, the equipment is considered to be failed to meet the requirements of Clause 6.202 without need for consequential testing. E 3: Parts likely to be impinged upon by the flame are sidered to be those within the envelope of a vertical der having a radius of 10 mm and a height equal to the ht of the flame, positioned above the point of the material porting, in contact with, or in close proximity to, nections. Sting of printed boards e base material of printed boards shall be jected to the needle-flame test of Clause 02.3. The flame shall be applied to the edge of board where the heat sink effect is lowest en the board is positioned as in normal use. a flame shall not be applied to an edge, sisting of broken perforations, unless the edge cass than 3 mm from a potential ignition source. A test is not carried out if— te printed board does not carry any potential tion source; the base material of printed boards, on which available apparent power at a connection eeds 15 VA operating at a voltage exceeding V and tal or less than 400 V (peak) a.c. or d.c. under mal operating conditions, is of flammability egory V-1 or better according to AS/NZS 695.11.10, or the printed boards are protected an enclosure meeting the flammability category	Result - Remark	Verdict
6.202.6	V-00 mei whii – th the excc 400 con sup aga V-00 prin hav fill t <i>Con</i> sma NOT pow resis pow disc For Pot volt	an enclosure meeting the flammability category according to AS/NZS 60695.11.10, or made of tal, having openings only for connecting wires ch fill the openings completely; or he base material of printed boards, on which available equipment power at a connection eeds 15 VA operating at a voltage exceeding 0 V (peak) a.c. or d.c. under normal operating ditions, and base material of printed boards porting spark gaps which provides protection inst overvoltages, is of flammability category according to AS/NZS 60695.11.10 or the ted boards are contained in a metal enclosure, ring openings only for connecting wires which he openings completely. <i>Informance shall be determined using the allest thickness of the material.</i> TE: Available apparent power is the maximum apparent er which can be drawn from the supplying circuit through a stive load whose value is chosen to maximize the apparent er for more than 2 min when the circuit supplied is onnected. Open circuit voltages greater than 4 kV ential ignition sources with open circuit ages exceeding 4 kV (peak) a.c. or d.c. under		N/A
	volt nor a F	ages exceeding 4 kV (peak) a.c. or d.c. under mal operating conditions shall be contained in IRE ENCLOSURE which shall comply with		N/A



Page 78 of 92

Report No. 180301431SHA-001

Clause		Requirement + Test	Result - Remark	Verdict
	flan AS/	nmability category V-1 or better according to //NZS 60695.11.10.	 	
8.6.1.201	8.6 MO MS desi ceil Tat safe whi inst acc The be = e wor - e ser To sec with	1.201 Instructional safeguard for fixed- unt television sets 2 and MS3 television sets and display devices igned only for fixed mounting to a wall of ing or equipment rack shall, where required in ole 36, footnote 201, have an instructional eguard in accordance with Clause F.5 ch may be on the equipment or included in the allation instructions or equivalent document ompanying the equipment. e elements of the instructional safeguard shall as follows: ement 1a: not available; ement 2: 'Stability Hazard' or equivalent rding; ement 3: 'The television set may fall, causing ious personal injury or death' or equivalent text; ement 4: the following or equivalent text: prevent injury, this television set must be urely attached to the floor/wall in accordance in the installation instructions		N/A
8.6.1.202	Res MS that shc as a equ dev 100 Wh inst for cor	Straining device 2 and MS3 television sets and display devices a are not solely fixed-mounted buld be provided with a restraining device such a fixing point to facilitate restraining the hipment from toppling forward. The restraining rice shall be capable of withstanding a pull of 0 N in all directions without damage. ere a restraining device is provided, ructions shall be provided in the instructions installation or instructions for use to ensure rect and safe installation.		N/A



Page 79 of 92

Report No. 180301431SHA-001

Appendix I Photograph of the Equipment under test (EUT)

GTM86100-1005-W2E-USB External view



GTM86100-1005-W2E-USB External view





Page 80 of 92



GTM86100-1005-W2A-USB External view

GTM86100-1005-W2A-USB External view





Page 81 of 92

GTM86100-1005-W2E-USB Internal view - Component side view of PCB



GTM86100-1005-W2E-USB Internal view – Soldering side view of PCB





Page 82 of 92

External view of transformer



External view of transformer





Page 83 of 92



Primary winding view of mains transformer





Page 84 of 92

Secondary winding view of mains transformer (TIW)









Transformer



Bobbin view of transformer





Page 86 of 92

GTM86100-1005-W2E External view



GTM86100-1005-W2E External view





GTM86100-1005-W2A External view



GTM86100-1005-W2A External view





Page 88 of 92

GTM86100-1005-W2E Internal view - Component side view of PCB



GTM86100-1005-W2E Internal view - Soldering side view of PCB





Page 89 of 92

External view of transformer







Page 90 of 92



Transformer





Page 91 of 92

Secondary winding view of mains transformer (TIW)







Page 92 of 92

Primary winding view of mains transformer



Bobbin view of transformer

